


Small Signal Transistors

TO-18 Case (Continued)



| TYPE NO. | DESCRIPTION | BV _{CBO} | BV _{CEO} | BV _{EBO} | I _{CBO} @ | V _{CB} | h _{FE} | | @ I _C | @ V _{CE} | V _{CE} (SAT) @ I _C | | C _{ob} | f _T | NF | t _{on} | t _{off} |
|----------|-----------------|-------------------|-------------------|-------------------|--|-----------------|-----------------|-----|------------------|-------------------|--|------------|-----------------|----------------|--------------|-----------------|------------------|
| | | (V) MIN | (V) MIN | (V) MIN | (μA) MAX *I _{CES} **I _{CEV} | | (V) | MIN | MAX | (mA) | (V) | (V) MAX | (mA) | (pF) MAX | (MHz) MIN | (dB) MAX | (ns) MAX |
| 2N957 | NPN RF/IF OSC | 40 | 20 | 5.0 | -- | -- | 45 | -- | 10 | 10 | -- | -- | 6.0 | 200 | -- | -- | -- |
| 2N978 | PNP AMPL/SWITCH | 30 | 20 | 5.0 | 5.0 | 10 | 15 | 60 | 150 | 10 | 1.5 | 150 | 45 | 40 | -- | -- | -- |
| 2N995 | PNP SAT SWITCH | 20 | 15 | 4.0 | 0.005 | 15 | 35 | 140 | 20 | 1.0 | 0.2 | 20 | 10 | 100 | -- | 65 | 125 |
| 2N996 | PNP SAT SWITCH | 15 | 12 | 4.0 | 0.005 | 10 | 35 | -- | 20 | 1.0 | 0.3 | 60 | 10 | 100 | -- | -- | -- |
| 2N1991 | PNP AMPL/SWITCH | 30 | 20 | 5.0 | 5.0 | 10 | 15 | 60 | 150 | 10 | 1.5 | 150 | 45 | 40 | -- | -- | -- |
| 2N2205 | NPN SAT SWITCH | 25 | 12 | 3.0 | 0.025 | 15 | 20 | -- | 10 | 1.0 | 0.22 | 10 | 6.0 | 200 | -- | 40 | 75 |
| 2N2220 | NPN AMPL/SWITCH | 60 | 35 | 5.0 | 0.01 | 50 | 20 | 60 | 150 | 10 | 0.4 | 150 | 8.0 | 250 | -- | -- | -- |
| 2N2221A | NPN AMPL/SWITCH | 75 | 40 | 6.0 | 0.01 | 60 | 40 | 120 | 150 | 10 | 0.3 | 150 | 8.0 | 250 | -- | -- | 285 |
| 2N2222A | NPN AMPL/SWITCH | 75 | 40 | 6.0 | 0.01 | 60 | 100 | 300 | 150 | 10 | 0.3 | 150 | 8.0 | 250 | -- | -- | 285 |
| 2N2242 | NPN SAT SWITCH | 15 | 15 | 5.0 | -- | -- | 40 | 120 | 10 | 1.0 | 0.3 | 10 | 6.0 | 250 | -- | -- | 25 |
| 2N2368 | NPN SAT SWITCH | 40 | 15 | 4.0 | 0.4 | 20 | 20 | 40 | 10 | 1.0 | 0.25 | 10 | 4.0 | 400 | -- | 12 | 15 |
| 2N2369A | NPN SAT SWITCH | 40 | 15 | 4.0 | -- | -- | 40 | 120 | 10 | 1.0 | 0.25 | 1.5 | 4.0 | 500 | -- | -- | 18 |
| 2N2377 | PNP AMPL/SWITCH | 25 | 25 | 10 | 1.0 | 25 | 15 | 120 | 1.0 | 6.0 | -- | -- | 12 | -- | -- | -- | -- |
| 2N2378 | PNP AMPL/SWITCH | 10 | 10 | 10 | 0.1 | 10 | 15 | -- | 5.0 | 0.5 | 0.15 | 5.0 | 12 | -- | -- | -- | -- |
| 2N2411 | PNP SAT SWITCH | 25 | 20 | 5.0 | 0.01 | 25 | 20 | 60 | 10 | 0.5 | 0.2 | 10 | 5.0 | 200 | -- | 25 | 100 |
| 2N2412 | PNP SAT SWITCH | 25 | 20 | 5.0 | 0.01 | 25 | 40 | 120 | 10 | 0.5 | 0.2 | 10 | 5.0 | 200 | -- | 25 | 100 |
| 2N2475 | NPN SAT SWITCH | 15 | 6.0 | 4.0 | 0.5 | 5.0 | 30 | 150 | 20 | 0.4 | 0.4 | 1.0 | 3.0 | 600 | -- | 20 | 15 |
| 2N2483 | NPN LOW NOISE | 60 | 60 | 6.0 | 0.01 | 45 | 40 | 120 | 0.01 | 5.0 | 0.35 | 1.0 | 6.0 | 60 | 4.0 | -- | -- |
| 2N2484 | NPN LOW NOISE | 60 | 60 | 6.0 | 0.01 | 45 | 100 | 500 | 0.01 | 5.0 | 0.35 | 1.0 | 6.0 | 60 | 2.0 | -- | -- |
| 2N2501 | NPN SAT SWITCH | 40 | 20 | 6.0 | -- | -- | 50 | 150 | 10 | 1.0 | 0.2 | 10 | 4.0 | 350 | -- | -- | -- |
| 2N2509 | NPN LOW NOISE | 124 | 80 | 7.0 | 0.005 | 100 | 25 | -- | 0.01 | 5.0 | 1.0 | 5.0 | 6.0 | 45 | 7.0 | -- | -- |
| 2N2510 | NPN LOW NOISE | 100 | 65 | 7.0 | 0.005 | 80 | 150 | 500 | 10 | 5.0 | 1.0 | 5.0 | 6.0 | 45 | 4.0 | -- | -- |
| 2N2511 | NPN LOW NOISE | 80 | 50 | 7.0 | 0.005 | 60 | 240 | 750 | 10 | 5.0 | 1.0 | 5.0 | 6.0 | 45 | 4.0 | -- | -- |
| 2N2539 | NPN SAT SWITCH | 60 | 30 | 5.0 | 0.25 | 40 | 50 | 150 | 150 | 10 | 0.45 | 150 | 8.0 | 250 | -- | 40 | 40 |
| 2N2540 | NPN SAT SWITCH | 60 | 30 | 5.0 | 0.25 | 40 | 100 | 300 | 150 | 10 | 0.45 | 150 | 8.0 | 250 | -- | 40 | 40 |
| 2N2586 | NPN LOW NOISE | 60 | 45 | 6.0 | 0.200 | 45 | 120 | 360 | 0.01 | 5.0 | 0.5 | 10 | 7.0 | 45 | 3.0 | -- | -- |
| 2N2645 | NPN AMPL/SWITCH | 75 | 40 | 7.0 | 0.01 | 60 | 100 | 300 | 150 | 10 | 0.4 | 10 | 25 | 50 | -- | -- | -- |
| 2N2651 | NPN SAT SWITCH | 40 | 20 | 5.0 | 0.03 | 20 | 25 | -- | 10 | 1.0 | 0.25 | 10 | 4.0 | 350 | -- | 35 | 75 |
| 2N2710 | NPN SAT SWITCH | 40 | 20 | 5.0 | 0.03 | 20 | 40 | -- | 10 | 1.0 | 0.25 | 10 | 4.0 | 500 | -- | 20 | 35 |
| 2N2837 | PNP AMPL/SWITCH | 50 | 35 | 5.0 | 0.1 | 30 | 30 | -- | 150 | 10 | 1.0 | 150 | 25 | 120 | -- | -- | -- |
| 2N2838 | PNP AMPL/SWITCH | 50 | 35 | 5.0 | 0.1 | 30 | 75 | -- | 150 | 10 | 1.0 | 150 | 25 | 120 | -- | -- | -- |
| 2N2845 | NPN SAT SWITCH | 60 | 30 | 5.0 | 0.2 | 30 | 30 | 120 | 150 | 10 | 1.0 | 500 | 8.0 | 250 | -- | 40 | 40 |
| 2N2847 | NPN SAT SWITCH | 60 | 20 | 5.0 | 0.2 | 30 | 40 | 140 | 150 | 10 | 0.75 | 500 | 8.0 | 250 | -- | 25 | 40 |
| 2N2861 | PNP LOW NOISE | 25 | 20 | 5.0 | -- | -- | 30 | 120 | 0.01 | 5.0 | 0.2 | 10 | 6.0 | 200 | 3.0 | -- | -- |
| 2N2862 | PNP LOW NOISE | 25 | 20 | 5.0 | -- | -- | 12 | 120 | 0.01 | 5.0 | 0.2 | 10 | 6.0 | 150 | 4.0 | -- | -- |
| 2N2894 | PNP SAT SWITCH | 12 | 12 | 4.0 | 0.08* | 6.0 | 40 | 150 | 30 | 0.5 | 0.5 | 100 | 6.0 | 400 | -- | 60 | 90 |
| 2N2894A | PNP SAT SWITCH | 12 | 12 | 4.0 | 0.05 | 10 | 30 | -- | 10 | 0.3 | 0.13 | 10 | 4.5 | 800 | -- | 20 | 25 |
| 2N2895 | NPN AMPL/SWITCH | 120 | 65 | 7.0 | -- | -- | 40 | 120 | 150 | 10 | 0.5 | 500 | 15 | 120 | -- | -- | -- |

(6-December 2004)



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.