

Small Signal Transistors

TO-92 Case (Continued)



TO-92



TO-92-18R

TYPE NO.	DESCRIPTION	LEAD CODE	V _{CB0}	V _{CEO}	V _{EBO}	I _{CB0} @	V _{CB}	h _{FE}		@ V _{CE}	@ I _C	V _{CE (SAT)} @ I _C		C _{ob}	f _T	NF	t _{off}	
			(V)	(V)	(V)	(nA)		(V)	MIN	MAX	(V)	(mA)	(V)	(mA)	(pF)	(MHz)	(dB)	
			MIN	*V _{CES} MIN	MAX	*I _{CES} *I _{CEV} MAX		MIN	MAX	MIN	MAX	MIN	MAX	MIN	MAX	*C _{rb} MAX	*TYP MIN	MAX
2N4401	NPN AMPL/SWITCH	EBC	60	40	6.0	100*	35	100	300	1.0	150	0.75	500	6.5	250	--	255	
2N4402	PNP AMPL/SWITCH	EBC	40	40	5.0	100*	35	50	150	2.0	150	0.75	500	8.5	150	--	255	
2N4403	PNP AMPL/SWITCH	EBC	40	40	5.0	100*	35	100	300	2.0	150	0.75	500	8.5	200	--	255	
2N4410	NPN LOW NOISE	EBC	120	80	5.0	10	100	60	400	1.0	10	0.20	1.0	12	60	--	--	
2N4424	NPN LOW NOISE	ECB	60	40	5.0	30	40	180	540	0.45	0.30	50	--	--	--	--	--	
2N4952	NPN AMPL/SWITCH	ECB	60	30	5.0	50	40	100	300	10	150	0.30	150	8.0	250	--	400	
2N4953	NPN AMPL/SWITCH	ECB	60	30	5.0	50	40	200	600	10	150	0.30	150	8.0	250	--	400	
2N5086	PNP LOW NOISE	EBC	50	50	3.0	10	10	150	500	5.0	0.10	0.30	10	4.0	40	3.0	--	
2N5087	PNP LOW NOISE	EBC	50	50	3.0	10	10	250	800	5.0	0.10	0.30	10	4.0	40	2.0	--	
2N5088	NPN LOW NOISE	EBC	35	30	4.5	50	20	300	900	5.0	0.10	0.50	10	4.0	50	3.0	--	
2N5089	NPN LOW NOISE	EBC	30	25	4.5	50	15	400	1,200	5.0	0.10	0.50	10	4.0	50	2.0	--	
2N5172	NPN LOW NOISE	ECB	25	25	5.0	100	25	100	500	10	10	0.25	10	13	200*	--	--	
2N5209	NPN LOW NOISE	EBC	50	50	4.5	50	35	100	300	5.0	0.10	0.70	10	4.0	30	3.0	--	
2N5210	NPN LOW NOISE	EBC	50	50	4.5	50	35	200	600	5.0	0.10	0.70	10	4.0	30	2.0	--	
2N5223	NPN AMPL/SWITCH	EBC	25	20	3.0	100	10	50	800	0.70	10	1.20	10	4.0	150	--	--	
2N5225	NPN AMPL/SWITCH	EBC	25	25	4.0	300	15	30	600	10	50	0.80	100	20	50	--	--	
2N5226	PNP AMPL/SWITCH	EBC	25	25	4.0	300	15	30	600	10	50	0.80	100	8.0	50	--	--	
2N5227	PN LOW NOISE	EBC	30	30	3.0	100	10	50	700	10	2.0	0.40	10	10	100	--	5.0	
2N5232A	NPN LOW NOISE	ECB	70	50	5.0	30	50	250	500	5.0	2.0	0.125	10	4.0	--	5.0	--	
2N5306	NPN DARLINGTON	ECB	25	25	12	100	25	7,000	70,000	5.0	2.0	1.40	200	10	60	--	--	
2N5308	NPN DARLINGTON	ECB	40	40	12	100	40	7,000	70,000	5.0	2.0	1.40	200	10	60	--	--	
2N5356	PNP AMPL/SWITCH	ECB	25	25	4.0	100	25	250	500	1.0	50	0.25	50	8.0	250*	--	--	
2N5366	PN AMPL/SWITCH	ECB	40	40	4.0	100	40	100	300	1.0	50	0.25	50	8.0	250*	--	--	
2N5367	PNP AMPL/SWITCH	ECB	40	40	4.0	100	40	250	500	1.0	50	0.25	50	8.0	250*	--	--	
2N5374	PNP AMPL/SWITCH	CBE†	60	30	5.0	50	40	200	400	10	150	0.30	150	10	150	--	--	
2N5375	PNP AMPL/SWITCH	CBE†	40	30	5.0	50	30	40	400	10	150	0.30	150	10	150	--	--	
2N5376	NPN AMPL/SWITCH	CBE†	60	30	5.0	10	30	120	--	5.0	1.0	--	--	8.0	--	--	--	
2N5377	NPN AMPL/SWITCH	CBE†	60	30	5.0	10	30	120	--	5.0	1.0	--	--	8.0	--	--	--	
2N5381	NPN AMPL/SWITCH	CBE†	60	40	6.0	50	30	100	300	1.0	10	12	10	4.0	300	5.0	--	
2N5383	PNP AMPL/SWITCH	CBE†	40	40	5.0	50	30	100	300	1.0	10	0.25	10	4.5	250	4.0	--	
2N5400	PNP HIGH VOLTAGE	EBC	130	120	5.0	100	100	40	180	5.0	10	0.50	50	6.0	100	8.0	--	
2N5401	PNP HIGH VOLTAGE	EBC	160	150	5.0	50	120	60	240	5.0	10	0.50	50	6.0	100	8.0	--	
2N5447	PNP AMPL/SWITCH	CBE†	40	25	5.0	100	20	60	300	5.0	50	0.25	50	12	100	--	--	
2N5448	PNP AMPL/SWITCH	CBE†	50	30	5.0	100	20	30	150	5.0	50	0.25	50	12	100	--	--	
2N5550	NPN HIGH VOLTAGE	EBC	160	140	6.0	100	100	60	250	5.0	10	0.25	50	6.0	100	10	--	
2N5551	NPN HIGH VOLTAGE	EBC	180	160	6.0	50	120	80	250	5.0	10	0.20	50	6.0	100	8.0	--	
2N5769	NPN SAT SWITCH	EBC	40	15	4.5	400	20	40	120	0.35	10	0.50	100	4.0	500	--	18	
2N5770	NPN RF OSC	EBC	30	15	3.0	10	15	50	200	1.0	8.0	0.40	10	1.1	800	--	--	
2N5771	PNP SAT SWITCH	EBC	15	15	4.5	10	8.0	50	120	0.30	10	0.60	50	3.0	850	--	20	
2N5772	NPN SAT SWITCH	EBC	40	15	5.0	500*	20	30	120	0.40	30	0.50	300	5.0	350	--	28	
2N5810	NPN AMPL/SWITCH	CBE†	35	25	5.0	100	25	60	200	2.0	2.0	0.75	500	15	100	--	--	
2N5811	PNP AMPL/SWITCH	CBE†	35	25	5.0	100	25	60	200	2.0	2.0	0.75	500	15	100	--	--	

Devices are available lead formed,
See pages 216 thru 219 for details.
Also available in Ammopack or Tape & Reel,
See pages 230 thru 235 for details.
† TO-92-18R



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.