

SOT89 PNP SILICON PLANAR DARLINGTON TRANSISTOR


ISSUE 3 – SEPTEMBER 1995



BCV48

COMPLEMENTARY TYPE – BCV49

PARTMARKING DETAIL – EE



ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	V_{CBO}	-80	V
Collector-Emitter Voltage	V_{CEO}	-60	V
Emitter-Base Voltage	V_{EBO}	-10	V
Peak Pulse Current	I_{CM}	-800	mA
Continuous Collector Current	I_C	-500	mA
Power Dissipation at $T_{amb}=25^\circ\text{C}$	P_{tot}	1	W
Operating and Storage Temperature Range	$T_j; T_{stg}$	-65 to +150	$^\circ\text{C}$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^\circ\text{C}$ unless otherwise stated).

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	CONDITIONS.
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	-80			V	$I_C = -100\mu\text{A}$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	-60			V	$I_C = -10\text{mA}^*$
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	-10			V	$I_E = -10\mu\text{A}$
Collector Cut-Off Current	I_{CBO}			-100 -10	nA μA	$V_{CB} = -60\text{V}$ $V_{CB} = -60\text{V}, T_{amb} = 150^\circ\text{C}$
Emitter Cut-Off Current	I_{EBO}			-100	nA	$V_{EB} = -4\text{V}$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$			-1	V	$I_C = -100\text{mA}, I_B = -0.1\text{mA}^*$
Base-Emitter Saturation Voltage	$V_{BE(sat)}$			-1.5	V	$I_C = -100\text{mA}, I_B = -0.1\text{mA}^*$
Static Forward Current Transfer Ratio	h_{FE}	2000 4000 10000 2000				$I_C = -100\mu\text{A}, V_{CE} = -1\text{V}^\dagger$ $I_C = -10\text{mA}, V_{CE} = -5\text{V}^*$ $I_C = -100\text{mA}, V_{CE} = -5\text{V}^*$ $I_C = -500\text{mA}, V_{CE} = -5\text{V}^*$
Transition Frequency	f_T		200		MHz	$I_C = -50\text{mA}, V_{CE} = -5\text{V}$ $f = 20\text{MHz}$
Output Capacitance	C_{obo}		4.5		pF	$V_{CB} = -10\text{V}, f = 1\text{MHz}$

* Measured under pulsed conditions. Pulse width=300 μs . Duty cycle $\leq 2\%$

\dagger Periodic Sample Test Only.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.