

# SOT23 N-CHANNEL ENHANCEMENT MODE VERTICAL DMOS FET


## BS170F

ISSUE 3 - JANUARY 1996

### FEATURES

- \* 60Volt  $V_{DS}$
- \*  $R_{DS(ON)} = 5\Omega$

PARTMARKING DETAIL – MV



SOT23

### ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Drain-Source Voltage	$V_{DS}$	60	V
Continuous Drain Current at $T_{amb}=25^{\circ}C$	$I_D$	0.15	mA
Pulsed Drain Current	$I_{DM}$	3	A
Gate Source Voltage	$V_{GS}$	$\pm 20$	V
Power Dissipation at $T_{amb}=25^{\circ}C$	$P_{tot}$	330	mW
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150	$^{\circ}C$

### ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$ unless otherwise stated).

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	CONDITIONS.
Drain-Source Breakdown Voltage	$BV_{DSS}$	60	90		V	$I_D=100\mu A, V_{GS}=0V$
Gate-Source Threshold Voltage	$V_{GS(th)}$	0.8		3	V	$I_D=1mA, V_{DS}=V_{GS}$
Gate-Body Leakage	$I_{GSS}$			10	nA	$V_{GS}=15V, V_{DS}=0V$
Zero Gate Voltage Drain Current	$I_{DSS}$			0.5	$\mu A$	$V_{DS}=25V, V_{GS}=0V$
Static Drain-Source On-State Resistance (1)	$R_{DS(on)}$			5	$\Omega$	$V_{GS}=10V, I_D=200mA$
Forward Transconductance (1)(2)	$g_{fs}$		200		mS	$V_{DS}=10V, I_D=200mA$
Input Capacitance (2)	$C_{iss}$		60		pF	$V_{DS}=10V, V_{GS}=0V, f=1MHz$
Turn-On Delay Time (2)(3)	$t_{d(on)}$			10	ns	$V_{DD}=-15V, I_D=600mA$
Turn-Off Delay Time (2)(3)	$t_{d(off)}$			10	ns	

(1) Measured under pulsed conditions. Width=300 $\mu s$ . Duty cycle  $\leq 2\%$  (2) Sample test.

(3) Switching times measured with 50 $\Omega$  source impedance and <5ns rise time on a pulse generator  
Spice parameter data is available upon request for this device

For typical characteristics graphs refer to ZVN3306F datasheet.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.