


SOT23 NPN SILICON PLANAR SMALL SIGNAL TRANSISTORS

FMMT5088 FMMT5089

ISSUE 2 - SEPTEMBER 1995

PARTMARKING DETAIL— FMMT5088 - 1Q
FMMT5089 - 1R

COMPLEMENTARY TYPES — FMMT5088 - FMMT5087
FMMT5089 - None Available



ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	FMMT5088	FMMT5089	UNIT
Collector-Base Voltage	V_{CBO}	35	30	V
Collector-Emitter Voltage	V_{CEO}	30	25	V
Emitter-Base Voltage	V_{EBO}	4.5	4.5	V
Continuous Collector Current	I_C	50	50	mA
Power Dissipation at $T_{amb}=25^{\circ}C$	P_{tot}	330	330	mW
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150		$^{\circ}C$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$).

PARAMETER	SYMBOL	FMMT5088		FMMT5089		UNIT	CONDITIONS.
		MIN.	MAX.	MIN.	MAX.		
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	35		25		V	$I_C=1mA, I_B=0$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	30		30		V	$I_C=100\mu A, I_E=0^*$
Collector- Base Cut-Off Current	I_{CBO}		50		50	nA nA	$V_{CB}=20V, I_E=0$ $V_{CB}=15V, I_E=0$
Emitter-Base Current	I_{EBO}		50		100	nA nA	$V_{EB(off)}=3V, I_C=0$ $V_{EB(off)}=4.5V, I_C=0$
Emitter Saturation Voltages	$V_{CE(sat)}$		0.5		0.5	V	$I_C=10mA, I_B=1mA$
	$V_{BE(sat)}$		0.8		0.8	V	
Static Forward Current Transfer Ratio	h_{FE}	300 350 300	900	400 450 400	1200		$I_C=100\mu A, V_{CE}=5V$ $I_C=1mA, V_{CE}=5V$ $I_C=10mA, V_{CE}=5V$
Transition Frequency	f_T	50		50		MHz	$I_C=500\mu A, V_{CE}=5V$ $f=20MHz$
Output Capacitance	C_{obo}		4		4	pF	$V_{CB}=5V, f=1MHz, I_E=0$
Emitter-base Capacitance	C_{ebo}		10		10	pF	$V_{BE}=0.5V, f=1MHz,$ $I_C=0$
Noise Figure	N		3		2	dB	$I_C=200mA, V_{CE}=5V,$ $R_o=10K\Omega, f=10Hz$ to 15KHz
Small Signal Current Transfer Ratio	h_{fe}	350	1400	450	1800		$I_C=1mA, V_{CE}=5V$ $f=1KHz$ ++

*Measured under pulsed conditions. Pulse width=300 μ s. Duty cycle \leq 2% ++ Periodic Sample test Only
Spice parameter data is available upon request for this device



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.