

Digital transistors (built-in resistor)


DTC323TU / DTC323TK / DTC323TS

●Features

In addition to the features of regular digital transistors,

- 1) Low $V_{CE(sat)}$ makes these transistors ideal for muting circuits.
(Typ. 0.04V at $I_C/I_B=50/2.5mA$)
- 2) They can be used at high current. ($I_{CMax.}=600mA$)

●Circuit schematic



●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Collector-base breakdown voltage	BV_{CBO}	30	—	—	V	$I_C=50\mu A$
Collector-emitter breakdown voltage	BV_{CEO}	15	—	—	V	$I_C=1mA$
Emitter-base breakdown voltage	BV_{EBO}	5	—	—	V	$I_E=50\mu A$
Collector cutoff current	I_{CBO}	—	—	0.5	μA	$V_{CB}=20V$
Emitter cutoff current	I_{EBO}	—	—	0.5	μA	$V_{EB}=4V$
Collector-emitter saturation voltage	$V_{CE(sat)}$	—	40	80	mV	$I_C/I_B=50mA/2.5mA$
DC current transfer ratio	h_{FE}	100	250	600	—	$I_C=50mA, V_{CE}=5V$
Input resistance	R_1	1.64	2.2	2.86	k Ω	—
Transition frequency	f_r	—	200	—	MHz	$V_{CE}=10V, I_E=-50mA, f=100MHz$ *
Output on resistance	R_{on}	—	0.65	—	Ω	$V_I=7V, R_L=1k\Omega, f=1kHz$

* Transition frequency of the device.

(96-348-C323T)

Digital transistors (built-in resistor)


DTC343TK / DTC343TS

●Features

In addition to the features of regular digital transistors,

- 1) Low $V_{CE(sat)}$ makes these transistors ideal for muting circuits.
(Typ. 0.04V at $I_C/I_B=50/2.5mA$)
- 2) They can be used at high current. ($I_{CMax.}=600mA$)

●Circuit schematic



●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Collector-base breakdown voltage	BV_{CBO}	30	—	—	V	$I_C=50\mu A$
Collector-emitter breakdown voltage	BV_{CEO}	15	—	—	V	$I_C=1mA$
Emitter-base breakdown voltage	BV_{EBO}	5	—	—	V	$I_E=50\mu A$
Collector cutoff current	I_{CBO}	—	—	0.5	μA	$V_{CB}=20V$
Emitter cutoff current	I_{EBO}	—	—	0.5	μA	$V_{EB}=4V$
Collector-emitter saturation voltage	$V_{CE(sat)}$	—	40	80	mV	$I_C=50mA, I_B=2.5mA$
DC current transfer ratio	h_{FE}	100	250	600	—	$I_C=50mA, V_{CE}=5V$
Input resistance	R_1	3.29	4.7	6.11	k Ω	—
Transition frequency	f_r	—	200	—	MHz	$V_{CE}=10V, I_E=-50mA, f=100MHz$ *
Output on resistance	R_{on}	—	0.95	—	Ω	$V_I=7V, R_L=1k\Omega, f=1kHz$

* Transition frequency of the device.

(94S-751-C343T)

●Absolute maximum ratings (Ta=25°C)

Parameter	Symbol	Limits	Unit
Collector-base voltage	V_{CBO}	30	V
Collector-emitter voltage	V_{CEO}	15	V
Emitter-base voltage	V_{EBO}	5	V
Collector current	I_C	600	mA
Collector power dissipation	DTC323TU / DTC323TK	200	mW
	DTC323TS	300	
Junction temperature	T_J	150	°C
Storage temperature	T_{stg}	-55~+150	°C

●Package, marking, and packaging specifications

Part No.	DTC323TU	DTC323TK	DTC323TS
Package	UMT3	SMT3	SPT
Marking	H02	H02	—
Packaging code	T106	T146	TP
Basic ordering unit (pieces)	3000	3000	5000

●Absolute maximum ratings (Ta=25°C)

Parameter	Symbol	Limits	Unit
Collector-base voltage	V_{CBO}	30	V
Collector-emitter voltage	V_{CEO}	15	V
Emitter-base voltage	V_{EBO}	5	V
Collector current	I_C	600	mA
Collector power dissipation	DTC343TK	200	mW
	DTC343TS	300	
Junction temperature	T_J	150	°C
Storage temperature	T_{stg}	-55~+150	°C

●Package, marking, and packaging specifications

Part No.	DTC343TK	DTC343TS
Package	SMT3	SPT
Marking	H03	—
Packaging code	T146	TP
Basic ordering unit (pieces)	3000	5000



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.