

# Small Signal Transistors

TO-18 Case (Continued)



TYPE NO.	DESCRIPTION	BV <sub>CBO</sub>	BV <sub>CEO</sub>	BV <sub>EBO</sub>	I <sub>CBO</sub> @	V <sub>CB</sub>	h <sub>FE</sub>		@ I <sub>C</sub>	@ V <sub>CE</sub>	V <sub>CE(SAT)</sub>	@ I <sub>C</sub>	C <sub>OB</sub>	f <sub>T</sub>	NF	t <sub>on</sub>	t <sub>off</sub>
		(V)	(V)	(V)	(μA)		(V)	MIN	MAX	(mA)	(V)	(V)		(mA)	(pF)	(MHz)	(dB)
		MIN	MIN	MIN	MAX						MAX		MAX	MIN	MAX	MAX	MAX
2N5183	NPN AMPL/SWITCH	18	18	7.0	0.5	12	75	400	10	10	0.5	300	20	125	--	--	--
2N6430	NPN HIGH VOLTAGE	200	200	6.0	0.1	160	50	200	30	10	0.5	20	4.0	50	--	--	--
2N6431	NPN HIGH VOLTAGE	300	300	6.0	0.1	200	50	200	30	10	0.5	20	4.0	50	--	--	--
2N6432	PNP HIGH VOLTAGE	200	200	5.0	0.25	160	30	150	30	10	0.5	20	6.0	50	--	--	--
2N6433	PNP HIGH VOLTAGE	300	300	5.0	0.25	200	30	150	30	10	0.5	20	6.0	50	--	--	--
BC110	NPN AMPL/SWITCH	80	80	8.0	0.1	80	30	--	2.0	5.0	0.6	50	5.0	50	--	--	--
BC187	PNP AMPL/SWITCH	30	25	5.0	0.1	30	140	--	2.0	5.0	--	--	--	--	--	--	--
BC393	PNP AMPL/SWITCH	180	180	6.0	0.05	100	50	100	10	10	0.3	10	7.0	5.0	--	100	400
BC394	NPN AMPL/SWITCH	180	180	6.0	0.05	100	50	100	10	10	0.3	10	7.0	5.0	--	100	400
BC477	PNP AMPL/SWITCH	90	80	6.0	0.01*	70	70	250	2.0	5.0	0.25	10	6.0	150	10	--	--
BCX22	NPN AMPL/SWITCH	125	125	5.0	0.1*	100	40	--	200	1.0	0.9	300	12	50	--	--	--
BCX23	PNP AMPL/SWITCH	125	125	5.0	0.1*	100	40	--	200	1.0	0.9	300	12	50	--	--	--
BCX24	NPN AMPL/SWITCH	100	100	7.0	0.03*	0.03*	20	--	10	1.0	0.9	300	12	30	--	--	--
BCX39	PNP AMPL/SWITCH	100	100	5.0	0.1*	100	40	--	200	1.0	0.9	300	12	50	--	--	--
BCX94	NPN AMPL/SWITCH	100	100	5.0	100*	100	63	--	100	1.0	0.9	300	8.0	50	--	--	--
BCY70	PNP AMPL/SWITCH	50	40	5.0	0.5	50	15	--	50	1.0	0.25	10	6.0	250	6.0	65	420
BCY71	PNP AMPL/SWITCH	45	45	5.0	0.5	45	100	600	10	1.0	0.25	10	6.0	250	2.0	--	--
BCY79	PNP AMPL/SWITCH	45	45	5.0	0.1*	45	80	1.0K	10	1.0	0.25	10	7.0	180	6.0	150	800
BFR16	NPN LOW NOISE	60	60	8.0	0.01*	50	150	490	1.0	5.0	5.0	10	6.0	70	4.0	--	--
BFW68	NPN AMPL/SWITCH	50	40	5.0	0.01	30	45	--	1.0	10	0.15	10	4.0	250	6.0	30	240
BFX65	PNP AMPL/SWITCH	45	45	6.0	0.01*	40	100	--	1.0	5.0	0.25	10	6.5	100	3.0	--	--
BFY18	NPN AMPL/SWITCH	40	25	3.0	0.01	20	25	--	10	9.0	1.5	10	5.5	200	--	--	--
BFY74	NPN AMPL/SWITCH	60	45	5.0	0.01	45	40	180	10	5.0	1.0	10	4.0	250	--	--	--
BFY76	NPN LOW NOISE	60	60	8.0	0.02*	50	150	300	1.0	5.0	0.35	1.0	6.0	70	4.0	--	--
BSV68	PNP AMPL/SWITCH	110	100	6.0	10	110	30	--	10	5.0	0.25	25	5.0	50	--	--	--
BSX19	NPN AMPL/SWITCH	40	15	--	0.4	20	20	60	10	1.0	0.25	10	4.0	400	--	12	15
BSX20	NPN AMPL/SWITCH	40	15	4.5	0.4	20	40	120	10	1.0	0.25	10	4.0	500	--	12	18
BSX21	NPN AMPL/SWITCH	120	80	5.0	0.2	90	20	--	4.0	1.0	0.70	4.0	4.5	60	--	--	--
BSX36	PNP AMPL/SWITCH	40	40	5.0	0.015	25	40	--	10	10	1.8	500	8.0	100	--	40	100
BSX49	NPN AMPL/SWITCH	60	40	5.0	0.07	50	25	--	100	1.0	1.0	500	6.0	250	--	50	95
BSX79	NPN AMPL/SWITCH	50	45	5.0	0.01	25	100	750	10	1.0	0.2	10	5.0	200	--	150	800
BSY18	NPN AMPL/SWITCH	20	12	5.0	1.0	20	40	120	10	0.35	0.28	10	5.0	280	--	16	24
BSY62	NPN AMPL/SWITCH	25	15	5.0	0.5	15	20	300	10	1.0	0.6	10	5.0	280	--	40	75
BSY79	NPN AMPL/SWITCH	120	--	5.0	0.05	90	30	--	1.0	1.0	0.5	2.0	4.0	50	--	--	--
BSY95A	NPN AMPL/SWITCH	20	15	5.0	0.05	16	50	200	10	0.35	0.35	10	6.0	200	--	--	--
MM4257	PNP FAST SWITCH	6.0	6.0	4.5	0.01*	6.0	30	120	10	0.3	0.15	10	3.0	500	--	25	25
MM4258	PNP FAST SWITCH	12	12	4.5	0.01*	6.0	30	120	10	0.3	0.15	10	3.0	700	--	25	30



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.