


6367254 MOTOROLA SC (XSTRS/R F)

96D 82624 D

T-31-25

**BF256,A,B,C**CASE 29-04, STYLE 23  
TO-92 (TO-226AA)**JFET**  
**VHF/UHF AMPLIFIER**

N-CHANNEL - DEPLETION

Refer to 2N4416 for graphs.

**MAXIMUM RATINGS**

Rating	Symbol	Value	Unit
Drain-Source Voltage	$V_{DS}$	$\pm 30$	Vdc
Drain-Gate Voltage	$V_{DG}$	30	Vdc
Gate-Source Voltage	$V_{GS}$	30	Vdc
Drain Current	$I_D$	100	mAdc
Forward Gate Current	$I_{G(f)}$	10	mAdc
Total Device Dissipation @ $T_A = 25^\circ\text{C}$ Derate above $25^\circ\text{C}$	$P_D$	360 2.88	mW mW/ $^\circ\text{C}$
Storage Channel Temperature Range	$T_{stg}$	-65 to +150	$^\circ\text{C}$

**ELECTRICAL CHARACTERISTICS** ( $T_A = 25^\circ\text{C}$  unless otherwise noted.)

Characteristic	Symbol	Min	Typ	Max	Unit
<b>OFF CHARACTERISTICS</b>					
Gate-Source Breakdown Voltage ( $I_G = 1.0 \mu\text{Adc}$ , $V_{DS} = 0$ )	$V_{(BR)GSS}$	30	—	—	Vdc
Gate-Source Voltage ( $V_{DS} = 15 \text{ Vdc}$ , $I_D = 200 \mu\text{A}$ )	$V_{GS(off)}$	0.5	—	7.5	Vdc
Gate Reverse Current ( $V_{GS} = 20 \text{ Vdc}$ , $V_{DS} = 0$ )	$I_{GSS}$	—	—	5	nAdc
<b>ON CHARACTERISTICS</b>					
Zero-Gate Voltage Drain Current ( $V_{DS} = 15 \text{ Vdc}$ , $V_{GS} = 0$ )	$I_{DSS}$				mAdc
	BF256(1)	3	—	18	
	BF256A	3	—	7	
	BF256B	6	—	13	
	BF256C	11	—	18	
<b>SMALL-SIGNAL CHARACTERISTICS</b>					
Forward Transfer Admittance ( $V_{DS} = 15 \text{ Vdc}$ , $V_{GS} = 0$ , $f = 1 \text{ kHz}$ )	$Y_{fs}$	4.5	5	—	mmhos
Reverse Transfer Capacitance ( $V_{DS} = 20 \text{ Vdc}$ , $-V_{GS} = 1 \text{ Vdc}$ , $f = 1 \text{ MHz}$ )	$C_{rss}$	—	0.7	—	pF
Output Capacitance ( $V_{DS} = 20 \text{ Vdc}$ , $V_{GS} = 0$ , $f = 1 \text{ MHz}$ )	$C_{oss}$	—	1.0	—	pF
Noise Figure ( $V_{DS} = 10 \text{ Vdc}$ , $R_S = 47 \Omega$ , $f = 800 \text{ MHz}$ )	$N_F$	—	7.5	—	db
Cut-off Frequency(2) ( $V_{DS} = 15 \text{ Vdc}$ , $V_{GS} = 0$ )	$f_{gfs}$	—	1000	—	MHz
Power Gain ( $V_{DS} = 15 \text{ Vdc}$ , $R_S = 47 \Omega$ , $f = 800 \text{ MHz}$ )	$G_p$	—	11	—	dB

(1) On orders against the BF256, any or all subgroups might be shipped.

(2) The frequency at which  $g_{fs}$  is 0.7 of its value at 1 kHz.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.