


# MICRO ELECTRONICS MICRO

## 2N4416,A

N-CHANNEL FET

CASE TO-72



2N4416 and 2N4416A are N-channel field-effect transistors designed for general purpose amplifier and chopper applications.

### ABSOLUTE MAXIMUM RATINGS :

		2N4416	2N4416A
Drain-Gate Voltage	V <sub>DG</sub>	30V	35V
Drain-Source Voltage	V <sub>DS</sub>	30V	35V
Reverse Gate-Source Voltage	V <sub>GS</sub>	30V	35V
Gate Current	I <sub>G</sub>		10mA
Total Power Dissipation @ T <sub>A</sub> =25°C	P <sub>tot</sub>		300mW
Operating Junction & Storage Temperature	T <sub>j</sub> , T <sub>stg</sub>		-65 to +200°C

### ELECTRICAL CHARACTERISTICS (T<sub>A</sub>=25°C unless otherwise specified)

PARAMETER	SYMBOL	MIN	MAX	UNIT	TEST CONDITIONS
Gate-Source Breakdown Voltage 2N4416 2N4416A	BV <sub>GSS</sub>	30 35		V	I <sub>G</sub> =1μA V <sub>DS</sub> =0
Gate-Source Forward Voltage	V <sub>GSF</sub>		1	V	I <sub>G</sub> =1mA V <sub>DS</sub> =0
Gate Reverse Current	I <sub>GSS</sub>		100 200	pA pA	V <sub>GS</sub> =20V V <sub>DS</sub> =0 V <sub>GS</sub> =20V V <sub>DS</sub> =0 T <sub>A</sub> =150°C
Gate-Source Cutoff Voltage 2N4416 2N4416A	V <sub>GS(off)</sub>	2.5	6 6	V	V <sub>DS</sub> =15V I <sub>D</sub> =1nA
Gate-Source Voltage	V <sub>GS</sub>	1	5.5	V	V <sub>DS</sub> =15V I <sub>D</sub> =0.5mA
Zero-Gate Voltage Drain Current	I <sub>DSS</sub>	5	15	mA	V <sub>DS</sub> =15V V <sub>GS</sub> =0
Small-Signal Common-Source Forward Transfer Admittance	Y <sub>fs</sub>	4.5	7.5	mmho	V <sub>DS</sub> =15V V <sub>GS</sub> =0 f=1KHz

MICRO ELECTRONICS LTD. 美科有限公司

38 Hung To Road, Kwun Tong, Kowloon, Hong Kong. Cable: Microtron, Hong Kong. Telex: 43510 Micro Hx.  
P.O. Box 9477, Kwun Tong. Tel: 3-430181-6, 3-893363, 3-892423, 3-898221 FAX: 3-410321



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.