


NPN SILICON PLANAR MEDIUM POWER TRANSISTORS

**2N6716
2N6717
2N6718**

ISSUE 1 – MARCH 94

FEATURES

- * 100 Volt V_{CE0}
- * Gain of 20 at $I_C = 0.5$ Amp
- * $P_{tot} = 1$ Watt



**E-Line
TO92 Compatible**

ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	2N6716	2N6717	2N6718	UNIT
Collector-Base Voltage	V_{CBO}	60	80	100	V
Collector-Emitter Voltage	V_{CEO}	60	80	100	V
Emitter-Base Voltage	V_{EBO}	5			V
Peak Pulse Current	I_{CM}	2			A
Continuous Collector Current	I_C	1			A
Power Dissipation at $T_{amb} = 25^\circ\text{C}$	P_{tot}	1			W
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +200			$^\circ\text{C}$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^\circ\text{C}$ unless otherwise stated).

PARAMETER	SYMBOL	2N6716		2N6717		2N6718		UNIT	CONDITIONS.
		MIN.	MAX	MIN.	MAX	MIN.	MAX		
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	60		80		100		V	$I_C = 0.1\text{mA}, I_E = 0$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	60		80		100		V	$I_C = 1\text{mA}, I_B = 0^*$
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	5		5		5		V	$I_E = 1\text{mA}, I_C = 0$
Collector Cut-Off Current	I_{CBO}		1		1		1	μA	$V_{CB} = 60\text{V}, I_E = 0$ $V_{CB} = 80\text{V}, I_E = 0$ $V_{CB} = 100\text{V}, I_E = 0$
Emitter Cut-Off Current	I_{EBO}		1		1		1	μA	$V_{EB} = 5\text{V}, I_C = 0$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$		0.5 0.35		0.5 0.35		0.5 0.35	V	$I_C = 250\text{mA}, I_B = 10\text{mA}^*$ $I_C = 250\text{mA}, I_B = 25\text{mA}^*$
Base-Emitter Turn-On Voltage	$V_{BE(on)}$		1.2		1.2		1.2	V	$I_C = 250\text{mA}, V_{CE} = 1\text{V}^*$
Static Forward Current Transfer Ratio	h_{FE}	80 50 20	250	80 50 20	250	80 50 20	250		$I_C = 50\text{mA}, V_{CE} = 1\text{V}^*$ $I_C = 250\text{mA}, V_{CE} = 1\text{V}^*$ $I_C = 500\text{mA}, V_{CE} = 1\text{V}^*$
Transition Frequency	f_T	50	500	50	500	50	500	MHz	$I_C = 50\text{mA}, V_{CE} = 10\text{V}$
Collector Base Capacitance	C_{CB}		30		30		30	pF	$V_{CE} = 10\text{V}, f = 1\text{MHz}$

*Measured under pulsed conditions. Pulse width=300 μs . Duty cycle $\leq 2\%$



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.