



# BIPOLAR TRANSISTOR MODULES

## Ratings and Specifications

### 20 High-speed switching 1400 volts class power transistor modules

- Suited for motor control applications with 575V AC input.
- Power transistors and free wheels are built into one package.
- Wide SOA with high-speed switching

Device type	V <sub>CB0</sub> Volts	V <sub>CEO</sub> Volts	V <sub>CEX</sub> (sus) Volts	I <sub>c</sub> cont. Amps.	P <sub>c</sub> Watts	h <sub>FE</sub> min.	(T <sub>j</sub> =125°C)		Switching time (Max.)			Package	Net mass Grams	Equivalent circuit Page 32, 33
							I <sub>c</sub> Amps.	V <sub>CE</sub> Volts	t <sub>on</sub> μsec.	t <sub>sig</sub> μsec.	t <sub>f</sub> μsec.			
2DI50Z-140	1400	1400	1200	50	400	75	50	2.8	3.0	15	2	M204	175	Fig. E4
2DI75Z-140	1400	1400	1200	75	500	75	75	2.8	3.0	15	2	M209	230	Fig. E4
2DI100Z-140	1400	1400	1200	100	800	75	100	2.8	3.0	15	2	M210	470	Fig. E5
2DI150Z-140	1400	1400	1200	150	1000	75	150	2.8	3.0	15	2	M210	470	Fig. E5
1DI300Z-140	1400	1400	1200	300	2000	75	300	2.8	3.0	15	2	M106	460	Fig. D2

### 21 Power transistor modules with zener diode for snubber circuit

- Built-in zener diode permits wiring connections in the snubber circuit to be simplified merely by connecting a power transistor module to an external capacitor.
- Two types of packages for the positive (P type) and negative (N type) legs allow the wiring distance between two power transistors to be shortened.
- Suited for parallel connection in the large capacity inverters

Device type	V <sub>CB0</sub> Volts	V <sub>CEO</sub> Volts	V <sub>CE0</sub> (sus) Volts	I <sub>c</sub> cont. Amps.	P <sub>c</sub> Watts	h <sub>FE</sub> min.	(T <sub>j</sub> =125°C)		Switching time (Max.)			Package	Net mass Grams	Equivalent circuit Page 33, 34
							I <sub>c</sub> Amps.	V <sub>CE</sub> Volts	t <sub>on</sub> μsec.	t <sub>sig</sub> μsec.	t <sub>f</sub> μsec.			
1DI300MN-050	600	600	450	300	1380	3000	300	2.5	5.5	8.0	2.0	M115	430	Fig. D8
1DI300MP-050	600	600	450	300	1380	3000	300	2.5	5.5	8.0	2.0	M114	430	Fig. D8
1DI400MN-050	600	600	450	400	1500	2000	400	2.5	8.5	8.0	2.0	M115	430	Fig. D8
1DI400MP-050	600	600	450	400	1500	2000	400	2.5	8.5	8.0	2.0	M114	430	Fig. D8
1DI300MN-120	1200	1200	900	300	2000	1500	300	4	7.0	15.0	3.0	M118	430	Fig. F2
1DI300MP-120	1200	1200	900	300	2000	1500	300	4	7.0	15.0	3.0	M117	430	Fig. F2
1DI400MN-120	1200	1200	900	400	3000	2000	400	4	3.0	15.0	3.0	M118	430	Fig. F2
1DI400MP-120	1200	1200	900	400	3000	2000	400	4	3.0	15.0	3.0	M117	430	Fig. F2
1DI200ZN-120	1200	1200	1200*	200	1400	100	200	5.0	3.0	15.0	2.0	M115	430	Fig. D9
1DI200ZP-120	1200	1200	1200*	200	1400	100	200	5.0	3.0	15.0	2.0	M114	430	Fig. D9
1DI300ZN-120	1200	1200	1200*	300	2000	100	300	5.0	3.0	15.0	2.0	M115	430	Fig. D9
1DI300ZP-120	1200	1200	1200*	300	2000	100	300	5.0	3.0	15.0	2.0	M114	430	Fig. D9

\* V<sub>CEX</sub> (sus)

### 22 Single in-line package/6 in one-package power transistor modules

- Allows devices to be reduced in size by high packaging density.
- High h<sub>FE</sub> transistors are built into MS type.

Device type	V <sub>CB0</sub> Volts	V <sub>CEO</sub> Volts	V <sub>CE0</sub> (sus) Volts	I <sub>c</sub> cont. Amps.	P <sub>c</sub> Watts	h <sub>FE</sub> min.	(T <sub>j</sub> =125°C) *		Switching time (Max.)			Package	Net mass Grams	Equivalent circuit Page 34, 36
							I <sub>c</sub> Amps.	V <sub>CE</sub> Volts	t <sub>on</sub> μsec.	t <sub>sig</sub> μsec.	t <sub>f</sub> μsec.			
6DI10MS-050	600	600	450	10	50	100	10	2	2.0	8	2	M615	65	Fig. H5
6DI15S-050	600	600	450	15	60	100	15	5	1.0	12	2	M614	40	Fig. H4
6DI15MS-050	600	600	450	15	60	150	15	2.5	2.0	8	2	M615	65	Fig. J7
6DI20MS-050	600	600	450	20	80	200	20	2.5	2.0	8	2	M615	65	Fig. J7

\* For 6DI15S-050 T<sub>j</sub> = 25°C.

This datasheet has been downloaded from:

[www.DatasheetCatalog.com](http://www.DatasheetCatalog.com)

Datasheets for electronic components.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.