

# SOT223 NPN SILICON PLANAR HIGH VOLTAGE TRANSISTOR

## FZT458


ISSUE 4 – JANUARY 1996

### FEATURES

\* 400 Volt  $V_{CE0}$

COMPLEMENTARY TYPE – FZT558

PARTMARKING DETAIL – FZT458



### ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	$V_{CBO}$	400	V
Collector-Emitter Voltage	$V_{CEO}$	400	V
Emitter-Base Voltage	$V_{EBO}$	5	V
Continuous Collector Current	$I_C$	300	mA
Peak Pulse Current	$I_{CM}$	1	A
Base Current	$I_B$	200	mA
Power Dissipation at $T_{amb}=25^{\circ}C$	$P_{tot}$	2	W
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150	$^{\circ}C$

### ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$ ).

PARAMETER	SYMBOL	MIN.	MAX.	UNIT	CONDITIONS.
Breakdown Voltages	$V_{(BR)CBO}$	400		V	$I_C=100\mu A$
	$V_{CEO(sus)}$	400		V	$I_C=10mA^*$
	$V_{(BR)EBO}$	5		V	$I_E=100\mu A$
Collector Cut-Off Currents	$I_{CBO}$		100	nA	$V_{CB}=320V$
	$I_{CES}$		100	nA	$V_{CE}=320V$
Emitter Cut-Off Current	$I_{EBO}$		100	nA	$V_{EB}=4V$
Emitter Saturation Voltages	$V_{CE(sat)}$		0.2 0.5	V	$I_C=20mA, I_B=2mA^*$ $I_C=50mA, I_B=6mA^*$
	$V_{BE(sat)}$		0.9	V	$I_C=50mA, I_B=5mA^*$
Base-Emitter Turn On Voltage	$V_{BE(on)}$		0.9	V	$I_C=50mA, V_{CE}=10V^*$
Static Forward Current Transfer Ratio	$h_{FE}$	100	300		$I_C=1mA, V_{CE}=10V$
		100			$I_C=50mA, V_{CE}=10V^*$
		15			$I_C=100mA, V_{CE}=10V^*$
Transition Frequency	$f_T$	50		MHz	$I_C=10mA, V_{CE}=20V$ $f=20MHz$
Collector-Base Breakdown Voltage	$C_{obo}$		5	pF	$V_{CB}=20V, f=1MHz$
Switching times	$t_{on}$		135 Typical	ns	$I_C=50mA, V_{CC}=100V$ $I_{B1}=5mA, I_{B2}=-10mA$
	$t_{off}$		2260 Typical	ns	

\*Measured under pulsed conditions. Pulse width=300 $\mu s$ . Duty cycle  $\leq 2\%$

Spice parameter data is available upon request for this device

For typical characteristics graphs see FMMT458 datasheet



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.