

NPN SILICON RF POWER TRANSISTOR

DESCRIPTION:

The ASI HF30-28S is Designed for

FEATURES:

- $P_G = 20$ dB min. at 30 W/30 MHz
- $IMD_3 = -30$ dBc max. at 30 W(PEP)
- **Omnigold™** Metalization System

MAXIMUM RATINGS

I_C	5.0 A
V_{CB}	65 V
V_{CE}	35 V
V_{EBO}	4.0 V
P_{DISS}	60 W @ $T_C = 25^\circ C$
T_J	$-65^\circ C$ to $+200^\circ C$
T_{STG}	$-65^\circ C$ to $+150^\circ C$
q_{JC}	$2.9^\circ C/W$

PACKAGE STYLE .380 4L STUD

DIM	MINIMUM inches / mm	MAXIMUM inches / mm
A	.220 / 5.59	.230 / 5.84
B	.980 / 24.89	
C	.370 / 9.40	.385 / 9.78
D	.004 / 0.10	.007 / 0.18
E	.320 / 8.13	.330 / 8.38
F	.100 / 2.54	.130 / 3.30
G	.450 / 11.43	.490 / 12.45
H	.090 / 2.29	.100 / 2.54
I	.155 / 3.94	.175 / 4.45
J		.750 / 19.05

ORDER CODE: ASI10605

CHARACTERISTICS $T_C = 25^\circ C$

SYMBOL	TEST CONDITIONS		MINIMUM	TYPICAL	MAXIMUM	UNITS
BV_{CBO}	$I_C = 10$ mA		65		---	V
BV_{CES}	$I_C = 200$ mA		65		---	V
BV_{CEO}	$I_C = 200$ mA		35		---	V
BV_{EBO}	$I_E = 10$ mA		4.0		---	V
I_{CES}	$V_{CE} = 30$ V		---		10	mA
I_{CBO}	$V_{CE} = 30$ V		---		1.0	mA
h_{FE}	$V_{CE} = 5.0$ V	$I_C = 500$ mA	5.0		200	---
C_{OB}	$V_{CB} = 30$ V	$f = 1.0$ MHz	---		65	pF
G_P	$V_{CE} = 28$ V	$P_{IN} = 7.0$ W	7.6		---	dB
h_c	$P_{OUT} = 30$ W(PEP)	$f = 175$ MHz	60		---	%



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.