

PNP Silicon Planar Transistor


BF 968

SIEMENS AKTIENGESELLSCHAFT

for input stages up to 900 MHz

BF 968 is a PNP silicon UHF planar transistor with passivated surface in a low-capacitance plastic package similar to TO 119 (50 B 3 DIN 41 867). The transistor is particularly suitable for use in low noise, gain-controlled input stages up to 900 MHz in tuners with diode tuning.

Type	Ordering code
BF 968	Q62702-F612



Approx. weight 0.25 g Dimensions in mm

Maximum ratings

Collector-emitter voltage	$-V_{CEO}$	35	V
Collector-base voltage	$-V_{CBO}$	40	V
Emitter-base voltage	$-V_{EBO}$	3	V
Collector current	$-I_C$	30	mA
Base current	$-I_B$	5	mA
Junction temperature	T_j	150	°C
Storage temperature range	T_{stg}	-55 to +150	°C
Total power dissipation	P_{tot}	160	mW

Thermal resistance

Junction to ambient air	R_{thJA}	600	K/W
-------------------------	------------	-----	-----

Static characteristics ($T_{amb} = 25^{\circ}\text{C}$)

Collector cutoff current ($-V_{CBO} = 15\text{ V}$)	$-I_{CBO}$	1 (<100)	nA
DC current gain ($-V_{CE} = 10\text{ V}; -I_C = 1\text{ mA}$)	h_{FE}	60 (>25)	-
Emitter cutoff current ($-I_C = 0; -V_{BE} = 3\text{ V}$)	$-I_{EBO}$	<10	μA

Dynamic characteristics ($T_{amb} = 25^{\circ}\text{C}$)

Transition frequency ($-I_C = 3\text{ mA}; -V_{CE} = 10\text{ V}; f = 100\text{ MHz}$)	f_T	1.1	GHz
Reverse transfer capacitance ($-V_{CE} = 1\text{ V}; f = 1\text{ MHz}$)	C_{12b}	0.1	pF
Collector-base capacitance ($-V_{CB} = 10\text{ V}; f = 1\text{ MHz}$)	$-C_{CBO}$	0.45	pF
Power gain ($-I_C = 3\text{ mA}; -V_{CB} = 10\text{ V}; f = 800\text{ MHz}; R_L = 500\ \Omega$)	G_{pb}	14.5	dB
Noise figure ($-I_C = 3\text{ mA}; -V_{CB} = 10\text{ V}; f = 800\text{ MHz}; R_g = 60\ \Omega$)	NF	3 (<4)	dB
Collector current for G_{pbmax} ($V_{CC} = 12\text{ V}; R_{CC} = 1\text{ k}\Omega; f = 800\text{ MHz}; R_L = 500\ \Omega$)	I_C	3.5	mA



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.