

MOS FIELD EFFECT POWER TRANSISTORS

2SJ327, 2SJ327-Z

SWITCHING

P-CHANNEL POWER MOS FET

INDUSTRIAL USE

DESCRIPTION

The 2SJ327 is P-channel MOS Field Effect Transistor designed for solenoid, motor and lamp driver.

FEATURES

- Low On-state Resistance
 $R_{DS(on)} = 0.13 \Omega$ TYP. ($V_{GS} = -10$ V, $I_D = -2$ A)
 $R_{DS(on)} = 0.21 \Omega$ TYP. ($V_{GS} = -4$ V, $I_D = -1.6$ A)
- Low C_{iss} $C_{iss} = 750$ pF TYP.
- Built-in G-S Gate Protection Diode

QUALITY GRADE

Standard

Please refer to "Quality grade on NEC Semiconductor Devices" (Document number IEI-1209) published by NEC Corporation to know the specification of quality grade on the devices and its recommended applications.

ABSOLUTE MAXIMUM RATINGS ($T_a = 25^\circ\text{C}$)


Drain to Source Voltage	V_{DSS}	-60	V
Gate to Source Voltage (AC)	V_{GSS}	± 20	V
Gate to Source Voltage (DC)	V_{GSS}	-20, +10	V
Drain Current (DC)	$I_{D(DC)}$	± 4.0	A
Drain Current (pulse)	$I_{D(pulse)^*}$	± 16	A
Total Power Dissipation ($T_c = 25^\circ\text{C}$)	P_{T1}	20	W
Total Power Dissipation ($T_a = 25^\circ\text{C}$)	P_{T2}	1.0	W
Channel Temperature	T_{ch}	150	$^\circ\text{C}$
Storage Temperature	T_{stg}	-55 to +150	$^\circ\text{C}$

* $PW \leq 10 \mu\text{s}$, Duty Cycle $\leq 1\%$



PACKAGE DIMENSIONS

in millimeters

2SJ327




2SJ327-Z




ELECTRICAL CHARACTERISTICS ($T_a = 25\text{ }^{\circ}\text{C}$)

CHARACTERISTIC	SYMBOL	MIN.	TYP.	MAX.	UNIT	TEST CONDITIONS
Drain to Source On-state Resistance	$R_{DS(on)}$		0.13	0.17	Ω	$V_{GS} = -10\text{ V}$, $I_D = -2.0\text{ A}$
Drain to Source On-state Resistance	$R_{DS(on)}$		0.21	0.34	Ω	$V_{GS} = -4\text{ V}$, $I_D = -1.6\text{ A}$
Gate to Source Cutoff Voltage	$V_{GS(off)}$	-1.0	-1.5	-2.0	V	$V_{DS} = -10\text{ V}$, $I_D = -1\text{ mA}$
Forward Transfer Admittance	$ y_{fs} $	3.0	3.8		S	$V_{DS} = -10\text{ V}$, $I_D = -2.0\text{ A}$
Drain Leakage Current	I_{DSS}			-10	μA	$V_{DS} = -60\text{ V}$, $V_{GS} = 0$
Gate to Source Leakage Current	I_{GSS}			± 10	μA	$V_{GS} = \pm 16\text{ V}$, $V_{DS} = 0$
Input Capacitance	C_{iss}		750		pF	$V_{DS} = -10\text{ V}$ $V_{GS} = 0$ $f = 1\text{ MHz}$
Output Capacitance	C_{oss}		410		pF	
Reverse Transfer Capacitance	C_{rss}		165		pF	
Turn-On Delay Time	$t_{d(on)}$		10		ns	$V_{GS(on)} = -10\text{ V}$ $V_{DD} = -30\text{ V}$ $I_D = -2.0\text{ A}$, $R_G = 10\text{ }\Omega$ $R_L = 15\text{ }\Omega$
Rise Time	t_r		35		ns	
Turn-Off Delay Time	$t_{d(off)}$		85		ns	
Fall Time	t_f		45		ns	
Total Gate Charge	Q_G		27		nC	$V_{GS} = -10\text{ V}$ $I_D = -4.0\text{ A}$ $V_{DD} = -48\text{ V}$
Gate to Source Charge	Q_{GS}		2		nC	
Gate to Drain Charge	Q_{GD}		11		nC	
Body Diode Forward Voltage	V_F		0.9		V	$I_F = 4.0\text{ A}$, $V_{GS} = 0$
Reverse Recovery Time	t_{rr}		85		ns	$I_F = 4.0\text{ A}$, $V_{GS} = 0$
Reverse Recovery Charge	Q_{rr}		130		nC	$di/dt = 50\text{ A}/\mu\text{s}$






Test Circuit 1: Switching Time














Test Circuit 2: Gate Charge



ELECTRICAL CHARACTERISTICS ($T_a = 25^\circ\text{C}$)







Reference

Application note name	No.
Safe operating area of Power MOS FET.	TEA-1034
Application circuit using Power MOS FET.	TEA-1035
Quality control of NEC semiconductors devices.	TEI-1202
Quality control guide of semiconductors devices.	MEI-1202
Assembly manual of semiconductors devices.	IEI-1207

No part of this document may be copied or reproduced in any form or by any means without the prior written consent of NEC Corporation. NEC Corporation assumes no responsibility for any errors which may appear in this document.

NEC Corporation does not assume any liability for infringement of patents, copyrights or other intellectual property rights of third parties by or arising from use of a device described herein or any other liability arising from use of such device. No license, either express, implied or otherwise, is granted under any patents, copyrights or other intellectual property rights of NEC Corporation or others.

The devices listed in this document are not suitable for use in aerospace equipment, submarine cables, nuclear reactor control systems and life support systems. If customers intend to use NEC devices for above applications or they intend to use "Standard" quality grade NEC devices for applications not intended by NEC, please contact our sales people in advance.

Application examples recommended by NEC Corporation.

Standard: Computer, Office equipment, Communication equipment, Test and Measurement equipment, Machine tools, Industrial robots, Audio and Visual equipment, Other consumer products, etc.

Special: Automotive and Transportation equipment, Traffic control systems, Antidisaster systems, Anticrime systems, etc.