

## P-CHANNEL J-FET

Qualified per MIL-PRF-19500/296

### Devices

**2N2609**


### Qualified Level

**JAN**

### ABSOLUTE MAXIMUM RATINGS ( $T_A = +25^{\circ}\text{C}$ unless otherwise noted)

Parameters / Test Conditions	Symbol	Value	Units
Gate-Source Voltage	$V_{GSS}$	30	V
Power Dissipation <sup>(1)</sup>	$P_D$	300	mW
Operating Junction & Storage Temperature Range	$T_{op}, T_{stg}$	-65 to +200	$^{\circ}\text{C}$

(1) Derate linearly 1.71 mW/ $^{\circ}\text{C}$  for  $T_A > +25^{\circ}\text{C}$ .



TO-18  
(TO-206AA)

\*See appendix A for package outline

### ELECTRICAL CHARACTERISTICS ( $T_A = +25^{\circ}\text{C}$ unless otherwise noted)

PARAMETERS / TEST CONDITIONS	Symbol	Min.	Max.	Units
Gate-Source Breakdown Voltage $V_{DS} = 0, I_G = 1.0 \mu\text{A}$	$V_{(BR)GSS}$	30		Vdc
Gate Reverse Current $V_{DS} = 0, V_{GS} = 30 \text{ Vdc}$ $V_{DS} = 0, V_{GS} = 15 \text{ Vdc}$	$I_{GSS}$		30 22.5	$\eta\text{A}$
Drain Current $V_{GS} = 0, V_{DS} = 5.0 \text{ Vdc}$	$I_{DDSS}$	-2.0	-10.0	mAdc
Gate-Source Cutoff Voltage $V_{DS} = 5.0 \text{ V}, I_D = 1.0 \mu\text{A}$	$V_{GS(off)}$	0.75	6.0	Vdc
Magnitude of Small-Signal, Common-Source Short-Circuit Forward Transfer Admittance $V_{GS} = 0, V_{DS} = 5.0 \text{ Vdc}, f = 1.0 \text{ kHz}$	$ Y_{fs2} $	2,000	6,250	$\mu\text{mho}$
Small-Signal, Common-Source Short-Circuit Input Capacitance $V_{GS} = 0, V_{DS} = 5.0 \text{ Vdc}, f = 1.0 \text{ MHz}$	$C_{iss}$		10	pF
Common-Source Spot Noise Figure $V_{GS} = 0, V_{DS} = 5.0 \text{ Vdc}, f = 1.0 \text{ kHz}$ $B_w = 16\%, R_G = 1.0 \text{ megohms}, e_{gen} = 1.82 \text{ mVdc}, R_L = 220 \Omega$	NF		3.0	dB



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.