

# SOT23 PNP SILICON PLANAR DARLINGTON TRANSISTORS

## BCV26 BCV46


ISSUE 3 – SEPTEMBER 1995

### FEATURES

- \* Low saturation voltage

COMPLEMENTARY TYPE – BCV26 - BCV27  
BCV46 - BCV47

PARTMARKING DETAILS – BCV26 - ZFD  
BCV46 - ZFE



### ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	BCV26	BCV46	UNIT
Collector-Base Voltage	$V_{CBO}$	-40	-80	V
Collector-Emitter Voltage	$V_{CEO}$	-30	-60	V
Emitter-Base Voltage	$V_{EBO}$	-10		V
Peak Pulse Current	$I_{CM}$	-800		mA
Continuous Collector Current	$I_C$	-500		mA
Base Current	$I_B$	-100		mA
Power Dissipation at $T_{amb}=25^{\circ}C$	$P_{tot}$	330		mW
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150		$^{\circ}C$

### ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$ unless otherwise stated).

PARAMETER	SYMBOL	BCV26		BCV46		UNIT	CONDITIONS.
		MIN.	MAX.	MIN.	MAX.		
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	-40		-80		V	$I_C=100\mu A$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	-30		-60		V	$I_C=10mA$ *
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	-10		-10		V	$I_E=10\mu A$
Collector Cut-Off Current	$I_{CBO}$		-100		-100	nA nA $\mu A$ $\mu A$	$V_{CB} = -30V$ $V_{CB} = -60V$ $V_{CB} = -30V, T_{amb} = 150^{\circ}C$ $V_{CB} = -60V, T_{amb} = 150^{\circ}C$
Emitter Base Cut-Off Current	$I_{EBO}$		-100		-100	nA	$V_{EB} = -4V$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$		-1.0		-1.0	V	$I_C = 100mA, I_B = -0.1mA$ *
Base-Emitter Saturation Voltage	$V_{BE(sat)}$		-1.5		-1.5	V	$I_C = 100mA, I_B = -0.1mA$ *
Static Forward Current Transfer Ratio	$h_{FE}$	4K 10K 20K 4K		2K 4K 10K 2K			$I_C = 100\mu A, V_{CE} = -1V \dagger$ $I_C = 10mA, V_{CE} = -5V$ * $I_C = 100mA, V_{CE} = -5V$ * $I_C = 500mA, V_{CE} = -5V$ *
Transition Frequency	$f_T$	200 Typical		200 Typical		MHz	$I_C = 50mA, V_{CE} = -5V$ $f = 20MHz$
Output Capacitance	$C_{obo}$	4.5 Typical		4.5 Typical		pF	$V_{CB} = -10V, f = 1MHz$

\*Measured under pulsed conditions. Pulse width=300 $\mu s$ . Duty cycle  $\leq 2\%$

Spice parameter data is available upon request for these devices † Periodic Sample Test Only.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.