

N-Channel Silicon Junction Field-Effect Transistor

• Audio Amplifier

Absolute maximum ratings at $T_A = 25^\circ\text{C}$

Reverse Gate Source & Reverse Gate Drain Voltage	- 40 V
Continuous Forward Gate Current	50 mA
Continuous Device Power Dissipation	360 mW
Power Derating	3.27 mW/°C

At 25°C free air temperature:

Static Electrical Characteristics

		J232			Unit	Process NJ16	
		Min	Typ	Max		Test Conditions	
Gate Source Breakdown Voltage	$V_{(BR)GSS}$	- 40			V	$I_G = -1\ \mu\text{A}, V_{DS} = 0\text{V}$	
Gate Reverse Current	I_{GSS}			- 250	pA	$V_{GS} = -30\text{V}, V_{DS} = 0\text{V}$	
Gate Operating Current	I_G		- 2		pA	$V_{DS} = 20\text{V}, I_D = 0\text{V}$	
Gate Source Cutoff Voltage	$V_{GS(OFF)}$	- 3		- 6	V	$V_{DS} = 20\text{V}, I_D = 1\ \mu\text{A}$	
Drain Saturation Current (Pulsed)	I_{DSS}	5		10	mA	$V_{DS} = 20\text{V}, V_{GS} = 0\text{V}$	

Dynamic Electrical Characteristics

Common Source Forward Transconductance	g_{fs}	2500		5000	μS	$V_{DS} = 20\text{V}, V_{GS} = 0\text{V}$	$f = 1\ \text{kHz}$
Common Source Output Conductance	g_{os}		5		μS	$V_{DS} = 20\text{V}, V_{GS} = 0\text{V}$	$f = 1\ \text{kHz}$
Common Source Input Capacitance	C_{iss}		4		pF	$V_{DS} = 20\text{V}, V_{GS} = 0\text{V}$	$f = 1\ \text{MHz}$
Common Source Reverse Transfer Capacitance	C_{rss}		1		pF	$V_{DS} = 20\text{V}, V_{GS} = 0\text{V}$	$f = 1\ \text{MHz}$
Equivalent Short Circuit Input Noise Voltage	\bar{e}_N		20	30	nV/ $\sqrt{\text{Hz}}$	$V_{DS} = 10\text{V}, V_{GS} = 0\text{V}$	$f = 10\ \text{Hz}$
			6		nV/ $\sqrt{\text{Hz}}$	$V_{DS} = 10\text{V}, V_{GS} = 0\text{V}$	$f = 1\ \text{kHz}$

TO-226AA Package

Dimensions in Inches (mm)

Pin Configuration

1 Drain, 2 Source, 3 Gate

Surface Mount

SMPJ232



This datasheet has been downloaded from:

www.DatasheetCatalog.com

Datasheets for electronic components.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.