To all our customers

Regarding the change of names mentioned in the document, such as Hitachi Electric and Hitachi XX, to Renesas Technology Corp.

The semiconductor operations of Mitsubishi Electric and Hitachi were transferred to Renesas Technology Corporation on April 1st 2003. These operations include microcomputer, logic, analog and discrete devices, and memory chips other than DRAMs (flash memory, SRAMs etc.) Accordingly, although Hitachi, Hitachi, Ltd., Hitachi Semiconductors, and other Hitachi brand names are mentioned in the document, these names have in fact all been changed to Renesas Technology Corp. Thank you for your understanding. Except for our corporate trademark, logo and corporate statement, no changes whatsoever have been made to the contents of the document, and these changes do not constitute any alteration to the contents of the document itself.

Renesas Technology Home Page: http://www.renesas.com

Renesas Technology Corp.
Customer Support Dept.
April 1, 2003

Cautions

Keep safety first in your circuit designs!

1. Renesas Technology Corporation puts the maximum effort into making semiconductor products better and more reliable, but there is always the possibility that trouble may occur with them. Trouble with semiconductors may lead to personal injury, fire or property damage.
   Remember to give due consideration to safety when making your circuit designs, with appropriate measures such as (i) placement of substitutive, auxiliary circuits, (ii) use of nonflammable material or (iii) prevention against any malfunction or mishap.

Notes regarding these materials

1. These materials are intended as a reference to assist our customers in the selection of the Renesas Technology Corporation product best suited to the customer's application; they do not convey any license under any intellectual property rights, or any other rights, belonging to Renesas Technology Corporation or a third party.
2. Renesas Technology Corporation assumes no responsibility for any damage, or infringement of any third-party's rights, originating in the use of any product data, diagrams, charts, programs, algorithms, or circuit application examples contained in these materials.
3. All information contained in these materials, including product data, diagrams, charts, programs and algorithms represents information on products at the time of publication of these materials, and are subject to change by Renesas Technology Corporation without notice due to product improvements or other reasons. It is therefore recommended that customers contact Renesas Technology Corporation or an authorized Renesas Technology Corporation product distributor for the latest product information before purchasing a product listed herein.
   The information described here may contain technical inaccuracies or typographical errors.
   Renesas Technology Corporation assumes no responsibility for any damage, liability, or other loss rising from these inaccuracies or errors.
   Please also pay attention to information published by Renesas Technology Corporation by various means, including the Renesas Technology Corporation Semiconductor home page (http://www.renesas.com).
4. When using any or all of the information contained in these materials, including product data, diagrams, charts, programs, and algorithms, please be sure to evaluate all information as a total system before making a final decision on the applicability of the information and products. Renesas Technology Corporation assumes no responsibility for any damage, liability or other loss resulting from the information contained herein.
5. Renesas Technology Corporation semiconductors are not designed or manufactured for use in a device or system that is used under circumstances in which human life is potentially at stake. Please contact Renesas Technology Corporation or an authorized Renesas Technology Corporation product distributor when considering the use of a product contained herein for any specific purposes, such as apparatus or systems for transportation, vehicular, medical, aerospace, nuclear, or undersea repeater use.
6. The prior written approval of Renesas Technology Corporation is necessary to reprint or reproduce in whole or in part these materials.
7. If these products or technologies are subject to the Japanese export control restrictions, they must be exported under a license from the Japanese government and cannot be imported into a country other than the approved destination.
   Any diversion or reexport contrary to the export control laws and regulations of Japan and/or the country of destination is prohibited.
8. Please contact Renesas Technology Corporation for further details on these materials or the products contained therein.

H5N5006FM

Silicon N Channel MOS FET
High Speed Power Switching

ADE-208-1112 (Z)
1st. Edition
Mar. 2001

Features

- Low on-resistance: $R_{DS(on)}$ = 2.5 Ω typ.
- Low leakage current: IDSS = 1 μA max (at VDS = 500 V)
- High speed switching: tf = 15 ns typ (at VGS = 10 V, VDD = 250 V, ID = 1.5 A)
- Low gate charge: Qg = 14 nC typ (at VDD = 400 V, VGS = 10 V, ID = 3 A)
- Avalanche ratings

Outline

TO-220FM



1. Gate
2. Drain
3. Source

Absolute Maximum Ratings (Ta = 25°C)

Item	Symbol	Ratings	Unit
Drain to source voltage	V_{DSS}	500	V
Gate to source voltage	V_{GSS}	±30	V
Drain current	I_D	3	A
Drain peak current	$I_{D\ (pulse)}$ Note1	12	A
Body-drain diode reverse drain current	I_{DR}	3	A
Body-drain diode reverse drain peak current	$I_{DR\ (pulse)}$ Note1	12	A
Avalanche current	I_{AP} Note3	3	A
Channel dissipation	Pch Note2	25	W
Channel to case Thermal Impedance	θ ch-c	5.0	°C/W
Channel temperature	Tch	150	°C
Storage temperature	Tstg	–55 to +150	°C

Notes: 1. PW ≤ 10 μs, duty cycle ≤ 1%
2. Value at Tc = 25°C
3. Tch ≤ 150°C

Electrical Characteristics (Ta = 25°C)

Item	Symbol	Min	Typ	Max	Unit	Test Conditions
Drain to source breakdown voltage	$V_{(BR)DSS}$	500	—	—	V	I_D = 10 mA, V_{GS} = 0
Gate to source leak current	I_{GSS}	—	—	±0.1	µA	V_{GS} = ±30 V, V_{DS} = 0
Zero gate voltage drain current	I_{DSS}	—	—	1	µA	V_{DS} = 500 V, V_{GS} = 0
Gate to source cutoff voltage	$V_{GS(off)}$	3.0	—	4.5	V	V_{DS} = 10 V, I_D = 1 mA
Static drain to source on state resistance	$R_{DS(on)}$	—	2.5	3.0	Ω	I_D = 1.5 A, V_{GS} = 10 V [Note4]
Forward transfer admittance	$\|y_{fs}\|$	1.5	2.5	—	S	I_D = 1.5 A, V_{DS} = 10 V [Note4]
Input capacitance	Ciss	—	365	—	pF	V_{DS} = 25 V
Output capacitance	Coss	—	35	—	pF	V_{GS} = 0
Reverse transfer capacitance	Crss	—	8	—	pF	f = 1 MHz
Turn-on delay time	td(on)	—	20	—	ns	I_D = 1.5 A
Rise time	tr	—	12	—	ns	V_{GS} = 10 V
Turn-off delay time	td(off)	—	48	—	ns	R_L = 167 Ω
Fall time	tf	—	15	—	ns	Rg = 10 Ω
Total gate charge	Qg	—	14	—	nC	V_{DD} = 400 V
Gate to source charge	Qgs	—	2	—	nC	V_{GS} = 10 V
Gate to drain charge	Qgd	—	8	—	nC	I_D = 3 A
Body-drain diode forward voltage	V_{DF}	—	0.85	1.3	V	I_F = 3 A, V_{GS} = 0
Body-drain diode reverse recovery time	trr	—	270	—	ns	I_F = 3 A, V_{GS} = 0
Body-drain diode reverse recovery charge	Qrr	—	0.8	—	µC	diF/dt = 100 A/µs

Note: 4. Pulse test

Main Characteristics

Power vs. Temperature Derating



Maximum Safe Operation Area



Typical Output Characteristics



Typical Transfer Characteristics



Drain to Source Saturation Voltage vs. Gate to Source Voltage



Static Drain to Source on State Resistance vs. Drain Current



Static Drain to Source on State Resistance vs. Temperature



Forward Transfer Admittance vs. Drain Current



Body-Drain Diode Rreverse Recovery Time



Typical Capacitance vs. Drain to Source Voltage



Dynamic Input Characteristics



Switching Characteristics



Reverse Drain Current vs.
Source to Drain Voltage



Gate to Source Cutoff Voltage
vs. Case Temperature



Switching Time Test Circuit



Waveform




Normalized Transient Thermal Impedance vs. Pulse Width
Tc = 25°C
D = 1
0.5
0.2
0.1
0.05
0.02
0.01
1shot pulse
θch – c(t) = γs (t) • θch – c
θch – c = 5.00°C/W, Tc = 25°C
PDM
D = PW / T
PW
T
Normalized Transient Thermal Impedance γs (t)
3
1
0.3
0.1
0.03
0.01
0.003
0.001
10 µ
100 µ
1 m
10 m
100 m
1
10
Pulse Width PW (s)

Package Dimensions

As of January, 2001

Unit: mm





Hitachi Code	TO-220FM
JEDEC	—
EIAJ	Conforms
Mass (reference value)	1.8 g

Cautions

1. Hitachi neither warrants nor grants licenses of any rights of Hitachi's or any third party's patent, copyright, trademark, or other intellectual property rights for information contained in this document. Hitachi bears no responsibility for problems that may arise with third party's rights, including intellectual property rights, in connection with use of the information contained in this document.
2. Products and product specifications may be subject to change without notice. Confirm that you have received the latest product standards or specifications before final design, purchase or use.
3. Hitachi makes every attempt to ensure that its products are of high quality and reliability. However, contact Hitachi's sales office before using the product in an application that demands especially high quality and reliability or where its failure or malfunction may directly threaten human life or cause risk of bodily injury, such as aerospace, aeronautics, nuclear power, combustion control, transportation, traffic, safety equipment or medical equipment for life support.
4. Design your application so that the product is used within the ranges guaranteed by Hitachi particularly for maximum rating, operating supply voltage range, heat radiation characteristics, installation conditions and other characteristics. Hitachi bears no responsibility for failure or damage when used beyond the guaranteed ranges. Even within the guaranteed ranges, consider normally foreseeable failure rates or failure modes in semiconductor devices and employ systemic measures such as fail-safes, so that the equipment incorporating Hitachi product does not cause bodily injury, fire or other consequential damage due to operation of the Hitachi product.
5. This product is not designed to be radiation resistant.
6. No one is permitted to reproduce or duplicate, in any form, the whole or part of this document without written approval from Hitachi.
7. Contact Hitachi's sales office for any questions regarding this document or Hitachi semiconductor products.

HITACHI

Hitachi, Ltd.
Semiconductor & Integrated Circuits.
Nippon Bldg., 2-6-2, Ohte-machi, Chiyoda-ku, Tokyo 100-0004, Japan
Tel: Tokyo (03) 3270-2111 Fax: (03) 3270-5109

URL NorthAmerica : http://semiconductor.hitachi.com/
Europe : http://www.hitachi-eu.com/hel/ecg
Asia : http://sicapac.hitachi-asia.com
Japan : http://www.hitachi.co.jp/Sicd/indx.htm

For further information write to:

Hitachi Semiconductor (America) Inc.
179 East Tasman Drive,
San Jose,CA 95134
Tel: <1> (408) 433-1990
Fax: <1>(408) 433-0223

Hitachi Europe GmbH
Electronic Components Group
Dornacher Straβe 3
D-85622 Feldkirchen, Munich
Germany
Tel: <49> (89) 9 9180-0
Fax: <49> (89) 9 29 30 00

Hitachi Europe Ltd.
Electronic Components Group.
Whitebrook Park
Lower Cookham Road
Maidenhead
Berkshire SL6 8YA, United Kingdom
Tel: <44> (1628) 585000
Fax: <44> (1628) 585160

Hitachi Asia Ltd.
Hitachi Tower
16 Collyer Quay #20-00,
Singapore 049318
Tel : <65>-538-6533/538-8577
Fax : <65>-538-6933/538-3877
URL : http://www.hitachi.com.sg

Hitachi Asia Ltd.
(Taipei Branch Office)
4/F, No. 167, Tun Hwa North Road,
Hung-Kuo Building,
Taipei (105), Taiwan
Tel : <886>-(2)-2718-3666
Fax : <886>-(2)-2718-8180
Telex : 23222 HAS-TP
URL : http://www.hitachi.com.tw

Hitachi Asia (Hong Kong) Ltd.
Group III (Electronic Components)
7/F., North Tower,
World Finance Centre,
Harbour City, Canton Road
Tsim Sha Tsui, Kowloon,
Hong Kong
Tel : <852>-(2)-735-9218
Fax : <852>-(2)-730-0281
URL : http://www.hitachi.com.hk

Copyright © Hitachi, Ltd., 2000. All rights reserved. Printed in Japan.
Colophon 2.0

RENESAS

littlediode
COMPONENTS FOR ALL

Littlediode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.