

# Power Transistor (−160V, −1.5A)

2SB1275 / 2SB1236A / 2SB1569A / 2SB1186A

●Features

- 1) High breakdown voltage. ( $V_{CE0} = -160V$ )
- 2) Low collector output capacitance. (Typ. 30pF at  $V_{CB} = 10V$ )
- 3) High transition frequency. ( $f_T = 50MHz$ )
- 4) Complements the 2SD1918 / 2SD1857A / 2SC2400A / 2SD1763A.

●Packaging specifications and hfe

Type	2SB1275	2SB1236A	2SB1569A	2SB1186A
Package	CPT3	ATV	TO-220FN	TO-220FP
hFE	NP	PQ	E	DE
Code	TL	TV2	—	—
Basic ordering unit (pieces)	2500	2500	500	500

●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Collector-base breakdown voltage	$BV_{CBO}$	-160	—	—	V	$I_C = -50 \mu A$
Collector-emitter breakdown voltage	$BV_{CEO}$	-160	—	—	V	$I_C = -1mA$
Emitter-base breakdown voltage	$BV_{EBO}$	-5	—	—	V	$I_E = -50 \mu A$
Collector cutoff current	$I_{CBO}$	—	—	-1	$\mu A$	$V_{CB} = -120V$
Emitter cutoff current	$I_{EBO}$	—	—	-1	$\mu A$	$V_{EB} = -4V$
Collector-emitter saturation voltage	$V_{CE(sat)}$	—	—	-2	V	$I_C/I_E = -1A/-0.1A$ *
Base-emitter saturation voltage	$V_{BE(sat)}$	—	—	-1.5	V	$I_C/I_E = -1A/-0.1A$ *
DC current transfer ratio	2SB1275	hFE	56	—	180	$V_{CE} = -5V, I_C = -1A$
	2SB1236A		82	—	270	
	2SB1569A		100	—	200	
	2SB1186A		60	—	200	
Transition frequency	$f_T$	—	50	—	MHz	$V_{CE} = -5V, I_E = 0.1A, f = 30MHz$
Output capacitance	$C_{ob}$	—	30	—	pF	$V_{CB} = -10V, I_E = 0A, f = 1MHz$

\* Measured using pulse current.

(96-612-A58)

# Power Transistor (160V, 1.5A)

2SD2211 / 2SD1918 / 2SD1857A / 2SD2400A / 2SD1763A

●Features

- 1) High breakdown voltage. ( $V_{CE0} = 160V$ )
- 2) Low collector output capacitance. (Typ. 20pF at  $V_{CB} = 10V$ )
- 3) High transition frequency. ( $f_T = 80MHz$ )
- 4) Complements the 2SB1275 / 2SB1236A / 2SB1569A / 2SB1186A.

●Packaging specifications and hfe

Type	2SD2211	2SD1918	2SD1857A	2SD2400A	2SD1763A
Package	MPT3	CPT3	ATV	TO-220FN	TO-220FP
hFE	Q	Q	PQ	E	DE
Marking	DQ*	—	—	—	—
Code	T100	TL	TV2	—	—
Basic ordering unit (pieces)	1000	2500	2500	500	500

\* Denotes hFE

●Electrical characteristics (Ta=25°C)

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Collector-base breakdown voltage	$BV_{CBO}$	160	—	—	V	$I_C = 50 \mu A$
Collector-emitter breakdown voltage	$BV_{CEO}$	160	—	—	V	$I_C = 1mA$
Emitter-base breakdown voltage	$BV_{EBO}$	5	—	—	V	$I_E = 50 \mu A$
Collector cutoff current	$I_{CBO}$	—	—	1	$\mu A$	$V_{CB} = 120V$
Emitter cutoff current	$I_{EBO}$	—	—	1	$\mu A$	$V_{EB} = 4V$
Collector-emitter saturation voltage	$V_{CE(sat)}$	—	—	2	V	$I_C/I_E = 1A/0.1A$ *
Base-emitter saturation voltage	$V_{BE(sat)}$	—	—	1.5	V	$I_C/I_E = 1A/0.1A$ *
DC current transfer ratio	2SD2211, 2SD1918	hFE	120	—	390	$V_{CE}/I_C = 5V/0.1A$
	2SD1857A		82	—	270	
	2SD2400A		100	—	200	
	2SD1763A		60	—	200	
Transition frequency	$f_T$	—	80	—	MHz	$V_{CE} = 5V, I_E = -0.1A, f = 30MHz$
Output capacitance	$C_{ob}$	—	20	—	pF	$V_{CB} = 10V, I_E = 0A, f = 1MHz$

\* Measured using pulse current.

●Absolute maximum ratings (Ta=25°C)

Parameter	Symbol	Limits	Unit	
Collector-base voltage	$V_{CBO}$	-160	V	
Collector-emitter voltage	$V_{CEO}$	-160	V	
Emitter-base voltage	$V_{EBO}$	-5	V	
Collector current	$I_C$	-1.5	A (DC)	
		-3	A (Pulse) *1	
Collector power dissipation	$P_C$	1	W ( $T_C = 25^\circ C$ )	
		10		
		1	W *2	
		2		
Junction temperature		TJ	150	$^\circ C$
Storage temperature		Tstg	-55 ~ +150	$^\circ C$

\*1 Single pulse  $P_w = 100ms$

\*2 Printed circuit board 1.7mm thick, collector plating  $1cm^2$  or larger.

●Absolute maximum ratings (Ta=25°C)

Parameter	Symbol	Limits	Unit	
Collector-base voltage	$V_{CBO}$	160	V	
Collector-emitter voltage	$V_{CEO}$	160	V	
Emitter-base voltage	$V_{EBO}$	5	V	
Collector current	$I_C$	1.5	A (DC)	
		3	A (Pulse) *1	
Collector power dissipation	$P_C$	1	W *2	
		2		
		1	W *3	
		10		
		2		
Junction temperature		TJ	150	$^\circ C$
Storage temperature		Tstg	-55 ~ +150	$^\circ C$

\*1 Single pulse  $P_w = 100ms$

\*2 Printed circuit board 1.7mm thick, collector plating  $1cm^2$  or larger.

\*3 When mounted on a 40 x 40 x 0.7mm ceramic board.

(96-744-C58)

This datasheet has been downloaded from:

[www.DatasheetCatalog.com](http://www.DatasheetCatalog.com)

Datasheets for electronic components.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.