

SOT89 NPN SILICON PLANAR HIGH VOLTAGE TRANSISTOR

FCX458


ISSUE 3 – OCTOBER 1995

FEATURES

- * 400 Volt V_{CE0}
- * $P_{tot} = 1$ Watt

COMPLEMENTARY TYPE – FCX558

PARTMARKING DETAIL – N58



ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	V_{CBO}	400	V
Collector-Emitter Voltage	V_{CEO}	400	V
Emitter-Base Voltage	V_{EBO}	5	V
Continuous Collector Current	I_C	225	mA
Peak Pulse Current	I_{CM}	500	mA
Power Dissipation at $T_{amb}=25^{\circ}C$	P_{tot}	1	W
Operating and Storage Temperature Range	T_j, T_{stg}	-65 to +150	$^{\circ}C$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$).

PARAMETER	SYMBOL	MIN.	MAX.	UNIT	CONDITIONS.
Breakdown Voltages	$V_{(BR)CBO}$	400		V	$I_C = 100\mu A$
	$V_{CEO(sus)}$	400		V	$I_C = 10mA^*$
	$V_{(BR)EBO}$	5		V	$I_E = 100\mu A$
Collector Cut-Off Currents	I_{CBO}		100	nA	$V_{CB} = 320V$
	I_{CES}		100	nA	$V_{CE} = 320V$
Emitter Cut-Off Current	I_{EBO}		100	nA	$V_{EB} = 4V$
Emitter Saturation Voltages	$V_{CE(sat)}$		0.2 0.5	V V	$I_C = 20mA, I_B = 2mA^*$ $I_C = 50mA, I_B = 6mA^*$
	$V_{BE(sat)}$		0.9	V	$I_C = 50mA, I_B = 5mA^*$
Base-Emitter Turn On Voltage	$V_{BE(on)}$		0.9	V	$I_C = 50mA, V_{CE} = 10V^*$
Static Forward Current Transfer Ratio	h_{FE}	100 100 15	300		$I_C = 1mA, V_{CE} = 10V$ $I_C = 50mA, V_{CE} = 10V^*$ $I_C = 100mA, V_{CE} = 10V^{**}$
Transition Frequency	f_T	50		MHZ	$I_C = 10mA, V_{CE} = 20V$ $f = 20MHZ$
Collector-Base Breakdown Voltage	C_{obo}		5	pF	$V_{CB} = 20V, f = 1MHZ$
Switching times	t_{on}	135 Typical		ns	$I_C = 50mA, V_C = 100V$ $I_{B1} = 5mA, I_{B2} = -10mA$
	t_{off}	2260 Typical		ns	

*Measured under pulsed conditions. Pulse width=300 μs . Duty cycle $\leq 2\%$

Spice parameter data is available upon request for this device

For typical characteristics graphs see FMMT458 datasheet



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.