

SOT23 NPN SILICON PLANAR HIGH VOLTAGE TRANSISTOR

FMMT6517

ISSUE 3 – NOVEMBER 1995

FEATURES


- * 350 Volt V_{CE0}
- * Gain of 15 at $I_C=100\text{mA}$

APPLICATIONS

- * SUITABLE FOR AMPLIFIER AND SWITCHING PRODUCTS

COMPLEMENTARY TYPE - FMMT6520

PARTMARKING DETAIL - 517



SOT23

ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	V_{CBO}	350	V
Collector-Emitter Voltage	V_{CEO}	350	V
Emitter-Base Voltage	V_{EBO}	5	V
Continuous Collector Current	I_C	500	mA
Power Dissipation at $T_{amb}=25^\circ\text{C}$	P_{tot}	330	mW
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150	$^\circ\text{C}$

ELECTRICAL CHARACTERISTICS (at $T_{amb}=25^\circ\text{C}$ unless otherwise stated).

PARAMETER	SYMBOL	MIN.	MAX.	UNIT	CONDITIONS.
Breakdown Voltages	$V_{(BR)CBO}$	350		V	$I_C=100\mu\text{A}, I_E=0$
	$V_{(BR)CEO}$	350		V	$I_C=1\text{mA}, I_B=0^*$
	$V_{(BR)EBO}$	5		V	$I_E=10\mu\text{A}, I_C=0$
Cut-Off Currents	I_{CBO}		50	nA	$V_{CB}=250\text{V}, I_E=0$
	I_{EBO}		50	nA	$V_{EB}=5\text{V}, I_C=0$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$		0.3	V	$I_C=10\text{mA}, I_B=1\text{mA}^*$
			0.35	V	$I_C=20\text{mA}, I_B=2\text{mA}^*$
			0.5	V	$I_C=30\text{mA}, I_B=3\text{mA}^*$
			1.0	V	$I_C=50\text{mA}, I_B=5\text{mA}^*$
Base-Emitter Saturation Voltage	$V_{BE(sat)}$		0.80	V	$I_C=10\text{mA}, I_B=1\text{mA}^*$
			0.85	V	$I_C=20\text{mA}, I_B=2\text{mA}^*$
			0.90	V	$I_C=30\text{mA}, I_B=3\text{mA}^*$
Base-Emitter Turn-On Voltage	$V_{BE(on)}$		2.0	V	$I_C=100\text{mA}, V_{CE}=10\text{V}^*$
Static Forward Current Transfer Ratio	h_{FE}	20			$I_C=1\text{mA}, V_{CE}=10\text{V}$
		30			$I_C=10\text{mA}, V_{CE}=10\text{V}^*$
		30	200		$I_C=30\text{mA}, V_{CE}=10\text{V}^*$
		20	200		$I_C=50\text{mA}, V_{CE}=10\text{V}^*$
		15			$I_C=100\text{mA}, V_{CE}=10\text{V}^*$
Output Capacitance	C_{obo}		6	pF	$V_{CB}=20\text{V}, f=1\text{MHz}$
Transition Frequency	f_T	50		MHz	$I_C=10\text{mA}, V_{CE}=20\text{V}, f=20\text{MHz}$

*Measured under pulsed conditions. Pulse width=300 μs . Duty cycle $\leq 2\%$



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.