

# NPN SILICON PLANAR MEDIUM POWER DARLINGTON TRANSISTOR


## FXT38C

ISSUE 1 – SEPT 93

### FEATURES

- \* 60 Volt  $V_{CEO}$
- \* Gain of 10K at  $I_C=0.5$  Amp

REFER TO BCX38 FOR GRAPHS



E-Line  
TO92 Compatible

### ABSOLUTE MAXIMUM RATINGS.

| PARAMETER                                  | SYMBOL         | VALUE       | UNIT        |
|--|----------------|-------------|-------------|
| Collector-Base Voltage                     | $V_{CBO}$      | 80          | V           |
| Collector-Emitter Voltage                  | $V_{CEO}$      | 60          | V           |
| Emitter-Base Voltage                       | $V_{EBO}$      | 10          | V           |
| Peak Pulse Current                         | $I_{CM}$       | 2           | A           |
| Continuous Collector Current               | $I_C$          | 800         | mA          |
| Power Dissipation at $T_{amb}=25^{\circ}C$ | $P_{tot}$      | 1           | W           |
| Operating and Storage Temperature Range    | $T_j; T_{stg}$ | -55 to +200 | $^{\circ}C$ |

### ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$ ).

| PARAMETER                             | SYMBOL         | MIN.          | TYP. | MAX. | UNIT | CONDITIONS.  |
|---------------------------------------|----------------|---------------|------|------|------|--|
| Collector-Base Breakdown Voltage      | $V_{(BR)CBO}$  | 80            |      |      | V    | $I_C=10\mu A, I_E=0$                                 |
| Collector-Emitter Sustaining Voltage  | $V_{CEO(sus)}$ | 60            |      |      | V    | $I_C=10mA, I_B=0$                                    |
| Emitter-Base Breakdown Voltage        | $V_{(BR)EBO}$  | 10            |      |      | V    | $I_E=10\mu A, I_C=0$                                 |
| Collector Cut-Off Current             | $I_{CBO}$      |               |      | 100  | nA   | $V_{CB}=60V, I_E=0$                                  |
| Emitter Cut-Off Current               | $I_{EBO}$      |               |      | 100  | nA   | $V_{EB}=8V, I_C=0$                                   |
| Collector-Emitter Saturation Voltage  | $V_{CE(sat)}$  |               |      | 1.25 | V    | $I_C=800mA, I_B=8mA^*$                               |
| Base-Emitter Turn-On Voltage          | $V_{BE(on)}$   |               |      | 1.8  | V    | $I_C=800mA, V_{CE}=5V^*$                             |
| Static Forward Current Transfer Ratio | $h_{FE}$       | 5000<br>10000 |      |      |      | $I_C=100mA, V_{CE}=5V^*$<br>$I_C=500mA, V_{CE}=5V^*$ |

\* Measured under pulsed conditions. Pulse width=300 $\mu s$ . Duty cycle  $\leq 2\%$



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.