

SOT23 SILICON PLANAR VARIABLE CAPACITANCE DIODES

**FMMV2101
to
FMMV2109**


ISSUE 3 - JANUARY 1996



PIN CONFIGURATION



PARTMARKING DETAILS
SEE TUNING CHARACTERISTICS



SOT23

ABSOLUTE MAXIMUM RATINGS.

| PARAMETER | SYMBOL | VALUE | UNIT |
|---|----------------|-------------|------------------|
| Reverse Voltage | V_R | 30 | V |
| Forward Current | I_F | 200 | mA |
| Power Dissipation at $T_{amb}=25^\circ\text{C}$ | P_{tot} | 330 | mW |
| Operating and Storage Temperature Range | $T_j; T_{stg}$ | -55 to +150 | $^\circ\text{C}$ |

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^\circ\text{C}$).

| PARAMETER | SYMBOL | MIN. | TYP. | MAX. | UNIT | CONDITIONS. |
|---|----------|------|------|------|-----------------------|---|
| Reverse Breakdown Voltage | V_{BR} | 30 | | | V | $I_R = 10\mu\text{A}$ |
| Reverse current | I_R | | | 20 | nA | $V_R = 25\text{V}$ |
| Series Inductance | L_S | | 3.0 | | nH | $f=250\text{MHz}$ Lead length $\approx 1.5\text{mm}$ |
| Diode Capacitance Temperature Coefficient | T_{CC} | | 280 | 400 | ppm/ $^\circ\text{C}$ | $V_R = 4\text{V}$, $f=1\text{MHz}$ Lead length $\approx 1.5\text{mm}$ |
| Case Capacitance | C_C | | 0.15 | | pF | $f=1\text{MHz}$ |

TUNING CHARACTERISTICS (at $T_{amb} = 25^\circ\text{C}$).

| Type No. | Nominal Capacitance (pF) $V_R = 4\text{V}$, $f=1\text{MHz}$ | | | Q - Figure of MERIT $V_R = 4\text{V}$, $f=50\text{MHz}$ | Turning Ratio C_2 / C_{30} $f=1\text{MHz}$ | | Partmark Detail |
|----------|---|------|------|---|--|------|-----------------|
| | Min. | Nom. | Max. | | Min. | Max. | |
| FMMV2101 | 6.1 | 6.8 | 7.5 | 450 | 2.5 | 3.3 | 6R |
| FMMV2103 | 9.0 | 10.0 | 11.0 | 400 | 2.6 | 3.3 | 6G |
| FMMV2104 | 10.8 | 12.0 | 13.2 | 400 | 2.6 | 3.3 | 6H |
| FMMV2105 | 13.5 | 15.0 | 16.5 | 400 | 2.6 | 3.3 | 6J |
| FMMV2107 | 19.8 | 22.0 | 24.2 | 350 | 2.7 | 3.3 | 6L |
| FMMV2108 | 24.3 | 27.0 | 29.7 | 300 | 2.7 | 3.3 | 6M |
| FMMV2109 | 29.3 | 33.0 | 36.3 | 280 | 2.7 | 3.3 | 6N |

* SELECTED DEVICE RANGE OFFERED ONLY



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.