


SOT23 PNP SILICON PLANAR GENERAL PURPOSE TRANSISTOR

FMMT4402 FMMT4403

ISSUE 2 - MARCH 1995



PARTMARKING DETAILS: FMMT4402 - 2K
FMMT4403 - 2L



ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	V_{CBO}	-40	V
Collector-Emitter Voltage	V_{CEO}	-40	V
Emitter-Base Voltage	V_{EBO}	-5	V
Continuous Collector Current	I_C	-600	A
Power Dissipation at $T_{amb}=25^{\circ}C$	P_{tot}	330	mW
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150	$^{\circ}C$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$ unless otherwise stated)

PARAMETER	SYMBOL	FMMT4402		FMMT4403		UNIT	CONDITIONS
		MIN.	MAX.	MIN.	MAX.		
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	-40		-40		V	$I_C=-1mA, I_B=0$
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	-40		-40		V	$I_C=-0.1mA, I_E=0$
Emitter-Base Breakdown Current	$V_{(BR)EBO}$	-5		-5		V	$I_E=-0.1mA, I_C=0$
Collector-Emitter Cut-Off Current	I_{CEX}		-0.1		-0.1	μA	$V_{CE}=-35V$ $V_{EB(off)}=-0.4V$
Base Cut-Off Current	I_{BEX}		-0.1		-0.1	μA	$V_{CE}=-35V$ $V_{EB(off)}=-0.4V$
Static Forward Current Transfer Ratio	h_{FE}	30 50 50 20	150	30 60 100 100 20	300		$I_C=-0.1mA, V_{CE}=-1V$ $I_C=-1mA, V_{CE}=-1V$ $I_C=-10mA, V_{CE}=-1V$ $I_C=-150mA, V_{CE}=-2V^*$ $I_C=-500mA, V_{CE}=-2V^*$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$		-0.4 -0.75		-0.4 -0.75	V V	$I_C=-150mA, I_B=-15mA^*$ $I_C=500mA, I_B=-50mA^*$
Base-Emitter Saturation Voltage	$V_{BE(sat)}$	-0.75	-0.95 -1.3	-0.75	-0.95 -1.3	V V	$I_C=-150mA, I_B=-15mA^*$ $I_C=500mA, I_B=-50mA$
Transition Frequency	f_T	150		200		MHz	$I_C=-20mA, V_{CE}=-10V$ $f=100MHz$
Output Capacitance	C_{obo}		8.5		8.5	pF	$V_{CB}=-10V, I_E=0$ $f=100kHz$
Input Capacitance	C_{ibo}		30		30	pF	$V_{BE}=0.5V$ $I_C=0, f=100kHz$

*Measured under pulsed conditions. Pulse width=300 μs . Duty cycle $\leq 2\%$

FMMT4402
FMMT4403

SWITCHING CHARACTERISTICS (at $T_{amb}= 25^{\circ}\text{C}$)

PARAMETER	SYMBOL	MIN.	MAX.	UNIT	CONDITIONS
Turn-On Time	t_{on}		35	ns	$V_{CC}=-30\text{V}$, $V_{BE(off)}=-2\text{V}$ $I_C=-150\text{mA}$, $I_{B1}=-15\text{mA}$ (See Fig.1)
Turn-Off Time	t_{off}		255	ns	$V_{CC}=-30\text{V}$, $I_C=-150\text{mA}$ $I_{B1}=I_{B2}=-15\text{mA}$ (See Fig. 2)



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.