


SOT23 PNP SILICON PLANAR SWITCHING TRANSISTORS

ISSUE 2 – SEPTEMBER 95

BSS80B BSS80C

PARTMARKING DETAIL — BSS80B - CH
BSS80C - CJ



ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	V_{CBO}	-60	V
Collector-Emitter Voltage	V_{CEO}	-40	V
Emitter-Base Voltage	V_{EBO}	-5	V
Peak Pulse Current	I_{CM}	-800	mA
Power Dissipation at $T_{amb}=25^{\circ}C$	P_{TOT}	330	mW
Operating and Storage Temperature Range	$t_j:t_{stg}$	-55 to +150	$^{\circ}C$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$).

PARAMETER		SYMBOL	MIN.	MAX.	UNIT	CONDITIONS.
Collector-Base Breakdown Voltage		$V_{(BR)CBO}$	-60		V	$I_C = -10\mu A$
Collector-Emitter Breakdown Voltage		$V_{(BR)CEO}$	-40		V	$I_C = -10mA$
Emitter-Base Breakdown Voltage		$V_{(BR)EBO}$	-5			$I_E = -10mA$
Collector Cut-Off Current		I_{CBO}		-10 -10	nA μA	$V_{CB} = -50V, V_{CE} = -50V, T_a = 150^{\circ}C$
Emitter Cut-Off Current		I_{EBO}		-10	nA	$V_{BE} = -3V$
Collector-Emitter Saturation Voltage		$V_{CE(sat)}$		-0.4 -1.6	mV V	$I_C = -150mA, V_{CE} = -10V$ $I_C = -150mA, V_{CE} = -10V$
Static Forward Current Transfer Ratio	BSS80B BSS80C	h_{FE}	40 100	120 300		$I_C = 150mA, V_{CE} = 10V$ $I_C = 150mA, V_{CE} = 10V$
Transition Frequency		f_T	200		MHz	$V_{CE} = -20V, I_C = -50mA$ $f = 100MHz$
Output Capacitance		C_{obo}		8	pF	$V_{CB} = -10V, f = 1MHz$
Delay Time		t_d		10	ns	$V_{CC} = -30V, I_C = -150mA$ $I_{B1} = -I_{B2} = -15mA$
Rise Time		t_r		40	ns	
Storage Time		t_s		80	ns	
Fall Time		t_f		30	ns	



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.