

# SOT223 NPN SILICON PLANAR MEDIUM POWER TRANSISTOR

## BCP68


ISSUE 3 – FEBRUARY 1996

### FEATURES

- \* Suitable for AF drivers and output stages
- \* High collector current and Low  $V_{CE(sat)}$

COMPLEMENTARY TYPE – BCP69

PARTMARKING DETAIL – BCP68  
BCP68 – 25



### ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	$V_{CBO}$	25	V
Collector-Emitter Voltage	$V_{CEO}$	20	V
Emitter-Base Voltage	$V_{EBO}$	5	V
Peak Pulse Current	$I_{CM}$	2	A
Continuous Collector Current	$I_C$	1	A
Power Dissipation at $T_{amb}=25^\circ\text{C}$	$P_{tot}$	2	W
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150	$^\circ\text{C}$

### ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^\circ\text{C}$ unless otherwise stated).

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	CONDITIONS.
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	25			V	$I_C=10\mu\text{A}$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	20			V	$I_C=30\text{mA}^*$
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	5			V	$I_E=10\mu\text{A}$
Collector Cut-Off Current	$I_{CBO}$			100 10	nA $\mu\text{A}$	$V_{CB}=25\text{V}$ $V_{CB}=25\text{V}, T_{amb}=150^\circ\text{C}$
Emitter Cut-Off Current	$I_{EBO}$			10	$\mu\text{A}$	$V_{EB}=5\text{V}$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$			0.5	V	$I_C=1\text{A}, I_B=100\text{mA}^*$
Base-Emitter Turn-On Voltage	$V_{BE(on)}$		0.6	1.0	V V	$I_C=5\text{A}, V_{CE}=10\text{V}^*$ $I_C=1\text{A}, V_{CE}=1\text{V}^*$
Static Forward Current Transfer Ratio	$h_{FE}$ BCP68 BCP68-25	50 63 160	250	400 400		$I_C=5\text{mA}, V_{CE}=10\text{V}^*$ $I_C=500\text{mA}, V_{CE}=1\text{V}^*$ $I_C=500\text{mA}, V_{CE}=1\text{V}^*$
Transition Frequency	$f_T$		100		MHz	$I_C=100\text{mA}, V_{CE}=5\text{V},$ $f=100\text{MHz}$

\*Measured under pulsed conditions. Pulse width=300 $\mu\text{s}$ . Duty cycle  $\leq 2\%$   
For typical characteristics graphs see FMMT449 datasheet.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.