


Small Signal NPN Transistors TO-72 Case



TYPE NO.	DESCRIPTION	V _{CBO}	V _{CEO}	V _{EBO}	I _{CBO} @	V _{CB}	h _{FE}		@ I _C	@ V _{CE}	V _{CE} (SAT) @ I _C		f _T	C _{ob}
		(V)	(V)	(V)	(μA)	(V)	MIN	MAX	(mA)	(V)	(V)	(mA)	(MHz)	*C _{cb} (pF)
		MIN	MIN	MIN	MAX						MAX		MIN	MAX
2N917	RF/IF OSCILLATOR	30	15	3.0	0.001	15	20	--	3.0	1.0	0.5	3.0	500	1.7
2N917A	RF/IF OSCILLATOR	30	15	3.0	--	--	20	200	3.0	10	--	--	600	1.7
2N918	RF/IF OSCILLATOR	30	15	3.0	0.01	15	20	--	3.0	1.0	0.4	10	600	1.7
2N998	DARLINGTON	100	60	15	0.01	90	1,600	8,000	10	5.0	1.8	100	60	30
2N2857	VHF/UHF OSC	30	15	2.5	0.01	15	30	150	3.0	1.0	--	--	1,000	1.0*
2N2865	RF/IF OSCILLATOR	25	13	3.0	0.01	15	20	200	4.0	10	0.4	10	600	2.5
2N3478	VHF/UHF LOW NOISE	30	15	2.0	0.02	1.0	25	150	2.0	8.0	--	--	750	1.0*
2N3839	VHF/UHF AMPL/OSC	30	15	2.5	0.01	15	30	150	3.0	1.0	--	--	1,000	1.0*
2N5179	VHF/UHF AMPL/OSC	20	12	2.5	0.02	15	25	250	3.0	1.0	0.4	10	900	1.0*
BFY90	VHF/UHF AMPL/OSC	30	15	2.5	0.01	15	20	125	25	1.0	--	--	1,000	1.5*

Shaded areas indicate Darlington.

Dual Transistors TO-71 Case

P_D @ T_A=25°C=360mW Total (Both Die Equal Power)



TYPE NO.	DESCRIPTION	V _{CBO}	V _{CEO}	V _{EBO}	I _{CBO} @	V _{CB}	h _{FE}		@ I _C	@ V _{CE}	V _{CE} (SAT) @ I _C		MATCHING	
		(V)	(V)	(V)	(nA)	(V)	MIN	MAX	(mA)	(V)	(V)	(mA)	h _{FE} %	V _{BE} (mV)
		MIN	MIN	MIN	MAX						MAX			
CEN741	NPN LOW NOISE	45	45	6.0	10	45	150	600	0.01	5.0	0.35	1.0	20	5.0
CEN832	PNP LOW NOISE	60	60	5.0	10	50	150	450	1.0	5.0	0.25	1.0	20	5.0



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.