


Small Signal Transistors

TO-46 Case



TYPE NO.	DESCRIPTION	BV _{CB0}	BV _{CEO}	BV _{EBO}	I _{CB0} @	V _{CB}	h _{FE}		@ I _C	@ V _{CE}	V _{CE} (SAT) @ I _C		C _{ob}	f _T	N _F	t _{off}
		(V)	(V)	(V)	(μA)	(V)			(mA)	(V)	(V)	(mA)	(pF)	(MHz)	(dB)	(ns)
		MIN	MIN	MIN	***ICEV		MIN	MAX			MAX		MAX	MIN	MAX	MAX
2N2604	PNP LOW NOISE	60	45	6.0	0.01	45	40	120	0.01	5.0	0.5	10	6.0	30	4.0	--
2N2605	PNP LOW NOISE	60	45	6.0	0.01	45	100	300	0.01	5.0	0.5	10	6.0	30	3.0	--
2N3485*	PNP AMPL/SWITCH	60	40	5.0	0.02	50	40	120	150	10	1.6	500	8.0	200	--	180
2N3485A*	PNP AMPL/SWITCH	60	60	5.0	0.01	50	40	120	150	10	1.6	500	8.0	200	--	180
2N3486*	PNP AMPL/SWITCH	60	40	5.0	0.02	50	100	300	150	10	1.6	500	8.0	200	--	180
2N3486A*	PNP AMPL/SWITCH	60	60	5.0	0.01	50	100	300	150	10	1.6	500	8.0	200	--	180
2N3508	NPN SAT SWITCH	40	20	6.0	0.2	20	40	120	10	1.0	0.45	100	4.0	500	--	28
2N3509*	NPN SAT SWITCH	40	20	6.0	0.2	20	100	300	10	1.0	0.45	100	4.0	500	--	28
2N3647*	NPN SAT SWITCH	40	10	6.0	0.025**	10	25	150	150	1.0	0.6	300	4.0	350	--	25
2N3648*	NPN SAT SWITCH	40	15	6.0	0.025**	10	30	120	150	1.0	0.8	500	4.0	450	--	18
2N3673*	NPN AMPL/SWITCH	60	50	5.0	0.01	50	75	225	150	10	1.6	500	9.0	200	--	100
2N3736*	NPN SAT SWITCH	50	30	5.0	0.2**	25	30	120	1,000	1.5	0.9	1,000	9.0	250	--	60
2N3737*	NPN SAT SWITCH	75	50	5.0	0.2**	40	20	80	1,000	1.5	0.9	1,000	9.0	250	--	60
2N4449*	NPN AMPL/SWITCH	40	15	4.5	0.4	20	40	--	10	1.0	0.18	10	4.0	500	--	12
2N5581*	NPN AMPL/SWITCH	75	40	6.0	0.01	50	40	120	150	10	1.6	500	8.0	250	--	285
2N5582	NPN AMPL/SWITCH	75	40	6.0	0.01	50	100	300	150	10	1.6	500	8.0	300	--	285

*Available on special order; please consult factory.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.