

Semitronics Corp.

## silicon transistors

silicon small signal transistors

general purpose — alloy

Type	Polarity	Power Dissipation @ 25°C (mW)	T <sub>J</sub> (°C)	BV <sub>CEO</sub> (volts)	BV <sub>CE-</sub> (volts)	h <sub>FE</sub> @ I <sub>C</sub>			V <sub>CE</sub> (SAT) @ I <sub>C</sub>		hf—	f— (MHz)	Case Style
						(Min.)	(Max.)	(mA)	(volts)	(mA)			
		NOTE 1		NOTE 2						NOTE 3		NOTE 4	
2N327A	PNP	385 (A)	160	50	40 (0)	9.0	22	3.0	0.3	5.0	—	—	TO-5
2N327B	PNP	385 (A)	200	50	40 (0)	9.0	22	3.0	0.3	5.0	—	—	TO-5
2N328A	PNP	385 (A)	160	50	35 (0)	18	44	3.0	0.5	10	—	—	TO-5
2N328B	PNP	385 (A)	200	50	35 (0)	18	44	3.0	0.5	10	—	—	TO-5
2N329A	PNP	385 (A)	160	50	30 (0)	36	88	3.0	0.6	15	—	—	TO-5
2N329B	PNP	385 (A)	200	50	30 (0)	36	88	3.0	0.6	15	—	—	TO-5
2N330A	PNP	385 (A)	160	50	30 (0)	—	—	—	—	—	—	—	—
2N325	PNP	250 (A)	200	40	25 (0)	—	—	—	0.5	5.0	12 (E)	0.8 (B)	TO-18
2N324	PNP	250 (A)	200	40	25 (0)	9.0	—	5.0	—	5.0	24 (E)	0.8 (B)	TO-18
2N325	PNP	250 (A)	200	50	40 (0)	—	—	—	0.5	5.0	10 (E)	0.8 (B)	TO-18
2N326	PNP	250 (A)	200	50	40 (0)	—	—	—	0.5	5.0	20 (E)	0.8 (B)	TO-18
2N327	PNP	250 (A)	200	70	60 (0)	—	—	—	0.5	5.0	8 (E)	0.8 (B)	TO-18
2N328	PNP	250 (A)	200	70	60 (0)	—	—	—	0.5	5.0	18 (E)	0.8 (B)	TO-18
2N335	PNP	250 (A)	160	50	40 (0)	9	22	—	0.3	5.0	—	—	TO-18
2N336	PNP	250 (A)	160	50	35 (0)	18	44	—	0.5	5.0	—	—	TO-18
2N337	PNP	250 (A)	160	50	30 (0)	36	88	—	0.6	5.0	—	—	TO-18
2N338	PNP	250 (A)	175	40	35 (0)	—	—	—	0.3	5.0	9.0 (E)	1.0 (B)	TO-18
2N339	PNP	250 (A)	175	40	35 (0)	—	—	—	0.3	5.0	18 (E)	2.0 (B)	TO-18
2N340	PNP	250 (A)	175	40	35 (0)	—	—	—	0.3	5.0	36 (E)	2.0 (B)	TO-18
2N1024	PNP	250 (A)	175	18	15 (U)	—	—	—	—	—	9.0 (E)	1.0 (B)	TO-5
2N1025	PNP	250 (A)	175	40	35 (U)	—	—	—	—	—	9.0 (E)	1.0 (B)	TO-5
2N1026	PNP	250 (A)	175	40	35 (U)	—	—	—	—	—	18 (E)	2.0 (B)	TO-5
2N1027	PNP	250 (A)	175	18	15 (U)	—	—	—	—	—	18 (E)	4.0 (B)	TO-5
2N1028	PNP	250 (A)	175	12	10 (U)	—	—	—	—	—	9.0 (E)	7.2 (T)	TO-5
2N1118	PNP	150 (A)	140	25	25 (U)	—	—	—	—	—	15 (E)	8.0 (M)	TO-5
2N1118A	PNP	150 (A)	140	25	25 (U)	—	25	15	—	—	15 (E)	8.0 (M)	TO-5
2N1119	PNP	150 (A)	140	10	10 (U)	15	—	15	0.15	5.0	—	7.2 (T)	TO-5
2N1219	PNP	250 (A)	175	30	25 (0)	18	—	5.0	—	—	—	5.0 (B)	TO-5
2N1220	PNP	250 (A)	175	30	25 (0)	—	—	—	0.5	—	—	2.0 (B)	TO-5
2N1221	PNP	250 (A)	175	30	25 (0)	—	—	—	—	—	18 (E)	5.0 (B)	TO-5
2N1222	PNP	250 (A)	175	30	25 (0)	—	—	—	—	—	9.0 (E)	2.0 (B)	TO-5
2N1223	PNP	250 (A)	175	40	40 (0)	—	—	—	—	—	6.0 (E)	—	TO-5
2N1228	PNP	400 (A)	160	15	15 (0)	—	—	—	0.2	10	14 (E)	—	TO-5
2N1229	PNP	400 (A)	160	15	15 (0)	—	—	—	0.2	10	28 (E)	—	TO-5
2N1230	PNP	400 (A)	160	35	35 (0)	—	—	—	0.2	10	14 (E)	—	TO-5
2N1231	PNP	400 (A)	160	35	35 (0)	—	—	—	0.2	10	28 (E)	—	TO-5
2N1232	PNP	400 (A)	160	60	60 (0)	—	—	—	0.2	10	14 (E)	—	TO-5
2N1233	PNP	400 (A)	160	60	60 (0)	—	—	—	0.2	10	28 (E)	—	TO-5
2N1234	PNP	400 (A)	160	110	110 (0)	—	—	—	0.2	10	14 (E)	—	TO-5
2N1236	PNP	1000 (A)	160	15	15 (0)	—	—	—	0.2	10	14 (E)	—	TO-1
2N1239	PNP	1000 (A)	160	15	15 (0)	—	—	—	0.2	10	28 (E)	—	TO-1
2N1240	PNP	1000 (A)	160	35	35 (0)	—	—	—	0.2	10	14 (E)	—	TO-1
2N1241	PNP	1000 (A)	160	35	35 (0)	—	—	—	0.2	10	28 (E)	—	TO-1
2N1242	PNP	1000 (A)	160	60	60 (0)	—	—	—	0.2	10	14 (E)	—	TO-1
2N1243	PNP	1000 (A)	160	60	60 (0)	—	—	—	0.2	10	28 (E)	—	TO-1
2N1244	PNP	1000 (A)	160	110	110 (0)	—	—	—	0.2	10	14 (E)	—	TO-1
2N1275	PNP	250 (A)	160	100	80 (0)	9	25	1.0	0.3	5.0	—	100* (B)	TO-5
2N1429	PNP	100 (A)	140	6	6 (0)	12	—	5.0	0.1	5.0	25 (E)	16 (T)	TO-5
2N1439	PNP	400 (A)	200	50	50 (0)	—	—	—	0.25	5.0	9.0 (E)	0.5 (B)	TO-5
2N1440	PNP	400 (A)	200	60	50 (0)	—	—	—	0.25	5.0	9.0 (E)	1.0 (B)	TO-5
2N1441	PNP	400 (A)	200	50	35 (0)	—	—	—	0.25	5.0	18 (E)	1.0 (B)	TO-5
2N1442	PNP	400 (A)	200	50	30 (0)	—	—	—	0.25	5.0	30 (E)	1.0 (B)	TO-5
2N1443	PNP	400 (A)	200	50	15 (0)	—	—	—	0.25	5.0	50 (E)	1.0 (B)	TO-5
2N1469	PNP	250 (A)	175	40	35 (U)	—	—	—	—	—	36 (E)	2.0 (B)	TO-5
2N1474	PNP	250 (A)	175	60	60 (U)	—	—	—	—	—	12 (E)	1.0 (B)	TO-5
2N1474A	PNP	250 (A)	175	60	60 (U)	—	—	—	—	—	18 (E)	2.0 (B)	TO-5
2N1475	PNP	250 (A)	175	60	60 (U)	—	—	—	—	—	36 (E)	1.0 (B)	TO-5
2N1476	PNP	250 (A)	175	100	100 (U)	—	—	—	—	—	12 (E)	1.0 (B)	TO-5
2N1477	PNP	250 (A)	175	100	100 (U)	—	—	—	—	—	30 (E)	1.0 (B)	TO-5
2N1623	PNP	250 (A)	160	50	20 (0)	9.0	40	1.0	0.3	5.0	—	100* (B)	TO-5
2N1643	PNP	250 (A)	160	25	25 (U)	10	25	1.00	—	—	—	—	TO-5
2N1654	PNP	250 (A)	160	100	80 (0)	20	45	1.0	0.3	5.0	—	100* (B)	TO-5
2N1655	PNP	250 (A)	160	125	100 (0)	10	22	1.0	0.3	5.0	—	100* (B)	TO-5
2N1656	PNP	250 (A)	160	125	100 (0)	20	45	1.0	0.3	5.0	—	100* (B)	TO-5
2N2175	PNP	100 (A)	175	6	6 (0)	30	—	.020	—	—	—	10 (T)	TO-5
2N2176	PNP	100 (A)	175	6	6 (0)	30	—	.020	—	—	—	10 (T)	TO-18
2N2177	PNP	100 (A)	160	6	6 (0)	15	—	.005	—	—	50 (E)	8.0 (B)	TO-5
2N2178	PNP	100 (A)	160	6	6 (0)	15	—	.005	—	—	50 (E)	8.0 (B)	TO-18
2N3342	PNP	250 (A)	175	20	8 (0)	30	—	5.0	0.1	5.0	—	—	TO-5
2N3343	PNP	25 (A)	175	25	8 (0)	20	—	.25	—	—	—	2.0 (T)	TO-5
2N3344	PNP	250 (A)	175	30	30 (0)	25	—	1.0	—	—	—	2.0 (T)	TO-5
2N3345	PNP	250 (A)	175	50	50 (0)	15	—	1.0	—	—	—	2.0 (T)	TO-5
2N3346	PNP	250 (A)	175	50	50 (0)	25	—	1.0	—	—	—	2.0 (T)	TO-5

\* KHz

**NOTES:**

The following notes define test conditions or parameters. They are inserted directly below their appropriate column headings throughout the transistor section.

NOTE 1 — (for Power Dissipation @ 25°C)

- A = Ambient Temperature
- C = Case Temperature
- J = Junction Temperature

NOTE 3 — (for hf—)

- E = Common Emitter
- B = Common Base
- C = Common Collector

NOTE 2 — (for BV<sub>CE-</sub>)

- O = Base Open
- R = Specified Resistance
- S = Base Shorted
- V = Used only when Voltage Bias is applied
- X = Base-Emitter Back Biased

NOTE 4 — (for f—)

- B = Common Base Cutoff
- E = Common Emitter Cutoff
- M = Minimum Frequency of Oscillations
- T = Current Gain-Bandwidth Product

This datasheet has been downloaded from:

[www.DatasheetCatalog.com](http://www.DatasheetCatalog.com)

Datasheets for electronic components.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.