

CentralTM Semiconductor Corp.

145 Adams Avenue, Hauppauge, NY 11788 USA
Tel: (631) 435-1110 • Fax: (631) 435-1824

Manufacturers of World Class Discrete Semiconductors

1N5518, A, B, C, D

THRU

1N5546, A, B, C, D

LOW LEAKAGE, LOW NOISE ZENER DIODE

JEDEC DO-35 CASE

DESCRIPTION

The Central Semiconductor 1N5518 Series types are Silicon Avalanche Zener Diodes designed for applications requiring low noise, low leakage, low current and low impedance.

MAXIMUM RATINGS ($T_A=50^\circ\text{C}$)

	SYMBOL	UNIT
Power Dissipation Operating and Storage	P_D	400 mW
Junction Temperature	T_J, T_{stg}	-65 TO +200 $^\circ\text{C}$

ELECTRICAL CHARACTERISTICS ($T_A=25^\circ\text{C}$ unless otherwise noted)

JEDEC Type No. (note 1)	Nominal Zener Voltage $V_Z@I_{ZT}$ (volts)	Test Current I_{ZT} (ma)	Max. Zener Impedance $Z_{ZT}@I_{ZT}$ (ohms) (Note 2)	Max. Reverse Leakage Current		Max. Noise Density at $I_Z=250\mu\text{A}$ N_p $\mu\text{V}/\text{rHz}$ (Note 4)	Max. Regulation Factor (Note 5)		Max. Regulator Current I_{ZM} (mAdc)	Reverse Surge Current I_r (Surge) (mA) (Note 6)	Maximum Temperature Coefficient (%/ $^\circ\text{C}$) (+25 to +125 $^\circ\text{C}$)
				I_R (μAdc) (Note 3)	V_R Volts		ΔV_Z (volts)	I_{ZL} (mAdc)			
1N5518	3.3	20	26	5.0	0.9	0.5	0.90	2.0	115	1800	- .07%
1N5519	3.6	20	24	3.0	0.9	0.5	0.90	2.0	105	1650	- .065
1N5520	3.9	20	22	1.0	0.9	0.5	0.85	2.0	98	1500	- .060
1N5521	4.3	20	18	3.0	1.0	0.5	0.75	2.0	88	1400	- .055 + .020
1N5522	4.7	10	22	2.0	1.5	0.5	0.60	1.0	81	1270	- .043 + .025
1N5523	5.1	5	26	2.0	2.0	0.5	0.65	0.25	75	1170	- .030 + .030
1N5524	5.6	3	30	2.0	3.0	1.0	0.30	0.25	68	1080	- .030 + .045
1N5525	6.2	1	30	1.0	4.5	1.0	0.20	0.01	61	965	+ .050
1N5526	6.8	1	30	1.0	5.5	1.0	0.10	0.01	56	870	+ .052
1N5527	7.5	1	35	0.5	6.0	2.0	0.05	0.01	51	810	+ .058
1N5528	8.2	1	40	0.5	6.5	4.0	0.05	0.01	46	740	+ .062
1N5529	9.1	1	45	0.1	7.0	4.0	0.05	0.01	42	650	+ .068
1N5530	10.0	1	60	0.05	8.0	4.0	0.10	0.01	38	600	+ .075
1N5531	11.0	1	80	0.05	9.0	5.0	0.20	0.01	35	540	+ .075
1N5532	12.0	1	90	0.05	9.5	10	0.20	0.01	32	500	+ .080
1N5533	13.0	1	90	0.01	10.5	15	0.20	0.01	29	470	+ .080
1N5534	14.0	1	100	0.01	11.5	20	0.20	0.01	27	850	+ .082
1N5535	15.0	1	100	0.01	12.5	20	0.20	0.01	25	800	+ .082
1N5536	16.0	1	100	0.01	13.0	20	0.20	0.01	24	750	+ .083
1N5537	17.0	1	100	0.01	14.0	20	0.20	0.01	22	700	+ .085
1N5538	18.0	1	100	0.01	15.0	20	0.20	0.01	21	665	+ .085
1N5539	19.0	1	100	0.01	16.0	20	0.20	0.01	20	630	+ .086
1N5540	20.0	1	100	0.01	17.0	20	0.20	0.01	19	600	+ .086
1N5541	22.0	1	100	0.01	18.0	20	0.25	0.01	17	541	+ .087
1N5542	24.0	1	100	0.01	20.0	20	0.30	0.01	16	511	+ .088
1N5543	25.0	1	100	0.01	21.0	20	0.35	0.01	15	481	+ .090
1N5544	28.0	1	100	0.01	23.0	20	0.40	0.01	14	431	+ .091
1N5545	30.0	1	100	0.01	24.0	20	0.45	0.01	13	400	+ .091
1N5546	33.0	1	100	0.01	28.0	20	0.50	0.01	12	360	+ .092

Note 1: Suffix denotes V_Z tolerance: none for $\pm 20\%$, A for $\pm 10\%$, B for $\pm 5\%$, C for $\pm 2\%$, D for $\pm 1\%$.

Note 2: Measured with 10%, 60 Hz AC superimposed on I_{ZT} .

Note 3: Measured at V_R as shown in the table.

Note 4: Measured from 1000 to 3000 Hz.

Note 5: Difference between V_Z at I_{ZT} and I_{ZL} .

Note 6: Peak current superimposed on I_{ZT} ; device will withstand a total of five surges at one minute intervals, each surge being a $\frac{1}{2}$ square wave pulse of 8.0 msec. duration or an equivalent $\frac{1}{2}$ sinewave with the same effective rms current.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.