

**Power Transistor (−120V, −1.5A)**

2SB1236 / 2SB1186

## ●Features

- 1) High breakdown voltage. ( $V_{CE0} = -120V$ )
- 2) Low collector output capacitance. (Typ. 30pF at  $V_{CB} = -10V$ )
- 3) High transition frequency. ( $f_T = 50MHz$ )
- 4) Complements the 2SD1857 / 2SD1763.

●Packaging specifications and  $h_{FE}$ 

Type	2SB1236	2SB1186
Package	ATV	TO-220FP
$h_{FE}$	QR	EF
Code	TV2	—
Basic ordering unit (pieces)	2500	500

●Absolute maximum ratings ( $T_a = 25^\circ C$ )

Parameter	Symbol	Limits	Unit
Collector-base voltage	$V_{CBO}$	−120	V
Collector-emitter voltage	$V_{CEO}$	−120	V
Emitter-base voltage	$V_{EBO}$	−5	V
Collector current	$I_C$	−1.5	A (DC)
		−3	A (Pulse) *1
Collector power dissipation	$P_C$	1	W *2
		2	
		20	
Junction temperature	$T_J$	150	$^\circ C$
Storage temperature	$T_{stg}$	−55~+150	$^\circ C$

\*1 Single pulse  $P_w = 100ms$ \*2 Printed circuit board 1.7mm thick, collector plating 1cm<sup>2</sup> or larger.●Electrical characteristics ( $T_a = 25^\circ C$ )

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Collector-base breakdown voltage	$BV_{CBO}$	−120	—	—	V	$I_C = -50 \mu A$
Collector-emitter breakdown voltage	$BV_{CEO}$	−120	—	—	V	$I_C = -1mA$
Emitter-base breakdown voltage	$BV_{EBO}$	−5	—	—	V	$I_E = -50 \mu A$
Collector cutoff current	$I_{CBO}$	—	—	−1	$\mu A$	$V_{CB} = -100V$
Emitter cutoff current	$I_{EBO}$	—	—	−1	$\mu A$	$V_{EB} = -4V$
Collector-emitter saturation voltage	$V_{CE(sat)}$	—	—	−2	V	$I_C/I_E = -1A/-0.1A$ *
Base-emitter saturation voltage	$V_{BE(sat)}$	—	—	−1.5	V	$I_C/I_B = -1A/-0.1A$ *
DC current transfer ratio	2SB1236	120	—	390	—	$V_{CE} = -5V, I_C = -1A$
	2SB1186	100	—	320	—	
Transition frequency	$f_T$	—	50	—	MHz	$V_{CE} = -5V, I_E = 0.1A, f = 30MHz$
Output capacitance	$C_{ob}$	—	30	—	pF	$V_{CB} = -10V, I_E = 0A, f = 1MHz$

\* Measured using pulse current.

(94L-268-A56)

**Power Transistor (120V, 1.5A)**

2SC4132 / 2SD1857 / 2SD2343 / 2SD1763

## ●Features

- 1) High breakdown voltage. ( $V_{CE0} = 120V$ )
- 2) Low collector output capacitance. (Typ. 20pF at  $V_{CB} = 10V$ )
- 3) High transition frequency. ( $f_T = 80MHz$ )
- 4) Complements the 2SB1236 / 2SB1186.

●Packaging specifications and  $h_{FE}$ 

Type	2SC4132	2SD1857	2SD2343	2SD1763
Package	MPT3	ATV	TO-126F	TO-220FP
$h_{FE}$	PQR	PQR	PQ	EF
Marking	CB*	—	—	—
Code	T100	TV2	—	—
Basic ordering unit (pieces)	1000	2500	1000	500

\* Denotes  $h_{FE}$ ●Absolute maximum ratings ( $T_a = 25^\circ C$ )

Parameter	Symbol	Limits	Unit
Collector-base voltage	$V_{CBO}$	120	V
Collector-emitter voltage	$V_{CEO}$	120	V
Emitter-base voltage	$V_{EBO}$	5	V
Collector current	$I_C$	2	A
		3	A *1
Collector power dissipation	$P_C$	0.5	W *2
		2	
		1	
		1.5	
		5	
Junction temperature	$T_J$	150	$^\circ C$
Storage temperature	$T_{stg}$	−55~+150	$^\circ C$

\*1 Single pulse  $P_w = 10ms$ 

\*2 When mounted on a 40×40×0.7mm ceramic board.

●Electrical characteristics ( $T_a = 25^\circ C$ )

Parameter	Symbol	Min.	Typ.	Max.	Unit	Conditions
Collector-base breakdown voltage	$BV_{CBO}$	120	—	—	V	$I_C = 50 \mu A$
Collector-emitter breakdown voltage	$BV_{CEO}$	120	—	—	V	$I_C = 1mA$
Emitter-base breakdown voltage	$BV_{EBO}$	5	—	—	V	$I_E = 50 \mu A$
Collector cutoff current	$I_{CBO}$	—	—	1	$\mu A$	$V_{CB} = 100V$
Emitter cutoff current	$I_{EBO}$	—	—	1	$\mu A$	$V_{EB} = 4V$
Collector-emitter saturation voltage	$V_{CE(sat)}$	—	—	0.4	V	$I_C/I_E = 1A/0.1A$ *
DC current transfer ratio	2SC4132, 2SD1857	82	—	390	—	$V_{CE}/I_C = 5V/0.1A$
	2SD2343	82	—	270	—	
	2SD1763	100	—	320	—	
Transition frequency	$f_T$	—	80	—	MHz	$V_{CE} = 5V, I_E = -0.1A, f = 30MHz$ *
Output capacitance	$C_{ob}$	—	20	—	pF	$V_{CB} = 10V, I_E = 0A, f = 1MHz$

\* Measured using pulse current.

(96-175-C56)

This datasheet has been downloaded from:

[www.DatasheetCatalog.com](http://www.DatasheetCatalog.com)

Datasheets for electronic components.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.