

NPN HIGH POWER SILICON TRANSISTOR

Qualified per MIL-PRF-19500/488

Devices

2N5671

2N5672

Qualified Level

JAN
JANTX
JANTXV

MAXIMUM RATINGS


Ratings	Symbol	2N5671	2N5672	Unit
Collector-Emitter Voltage	V_{CEO}	90	120	Vdc
Collector-Base Voltage	V_{CBO}	120	150	Vdc
Emitter-Base Voltage	V_{EBO}	7.0		Vdc
Base Current	I_B	10		Adc
Collector Current	I_C	30		Adc
Total Power Dissipation	P_T	@ $T_A = +25^{\circ}\text{C}$ ⁽¹⁾	6.0	W
		@ $T_C = +25^{\circ}\text{C}$ ⁽²⁾	140	W
Operating & Storage Temperature Range	T_{op}, T_{stg}	-65 to +200		$^{\circ}\text{C}$

THERMAL CHARACTERISTICS

Characteristics	Symbol	Max.	Unit
Thermal Resistance, Junction-to-Case	$R_{\theta JC}$	1.25	$^{\circ}\text{C}/\text{W}$

1) Derate linearly 34.2 mW/ $^{\circ}\text{C}$ for $T_A > +25^{\circ}\text{C}$

2) Derate linearly 800 mW/ $^{\circ}\text{C}$ for $T_C > +25^{\circ}\text{C}$



TO-3*
(TO-204AA)

*See appendix A for package outline

ELECTRICAL CHARACTERISTICS ($T_C = 25^{\circ}\text{C}$ unless otherwise noted)

Characteristics	Symbol	Min.	Max.	Unit
-----------------	--------	------	------	------

OFF CHARACTERISTICS

Collector-Emitter Breakdown Voltage $I_C = 200 \text{ mAdc}$	2N5671 2N5672	$V_{(BR)CEO}$	90 120	Vdc
Collector-Emitter Breakdown Voltage $I_C = 200 \text{ mAdc}$	2N5671 2N5672	$V_{(BR)CER}$	110 140	Vdc
Collector-Emitter Breakdown Voltage $I_C = 200 \text{ mAdc}$	2N5671 2N5672	$V_{(BR)CEX}$	120 150	Vdc
Collector-Emitter Cutoff Current $V_{CE} = 80 \text{ Vdc}$		I_{CEO}	10	mAdc
Collector-Emitter Cutoff Current $V_{CE} = 110 \text{ Vdc}, V_{BE} = 1.5 \text{ Vdc}$	2N5671	I_{CEX}	12	mAdc
$V_{CE} = 135 \text{ Vdc}, V_{BE} = 1.5 \text{ Vdc}$	2N5672			

2N5671, 2N5672 JAN SERIES

ELECTRICAL CHARACTERISTICS (con't)

Characteristics	Symbol	Min.	Max.	Unit
-----------------	--------	------	------	------

OFF CHARACTERISTICS (con't)

Collector-Base Cutoff Current V _{CB} = 120 Vdc V _{CB} = 150 Vdc	2N5671 2N5672	I _{CBO}	25 25	mA _{dc}
Emitter-Base Cutoff Current V _{EB} = 7.0 Vdc		I _{EBO}	10	mA _{dc}

ON CHARACTERISTICS ⁽³⁾

Forward-Current Transfer Ratio I _C = 15 Adc, V _{CE} = 2.0 Vdc I _C = 20 Adc, V _{CE} = 5.0 Vdc		h _{FE}	20 20	100	
Collector-Emitter Saturation Voltage I _C = 15 Adc, I _B = 1.2 Adc I _C = 30 Adc, I _B = 6.0 Adc		V _{CE(sat)}		0.75 5.0	Vdc
Base-Emitter Saturation Voltage I _C = 15 Adc, I _B = 1.2 Adc		V _{BE(sat)}		1.5	Vdc

DYNAMIC CHARACTERISTICS

Magnitude of Common Emitter Small-Signal Short-Circuit Forward Current Transfer Ratio I _C = 2.0 Adc, V _{CE} = 10 Vdc, f = 5.0 MHz		h _{fe}	10	40	
Output Capacitance V _{CB} = 10 Vdc, I _E = 0, 100 kHz ≤ f ≤ 1.0 MHz		C _{obo}		900	pF

SWITCHING CHARACTERISTICS

Turn-On Time V _{CC} = 30 ± 2.0 Vdc; I _C = 15 Adc; I _{B1} = 1.2 Adc		t _{on}		0.5	μs
Turn-Off Time V _{CC} = 30 ± 2.0 Vdc; I _C = 15 Adc; I _{B1} = I _{B2} = 1.2 Adc		t _{off}		1.5	μs

SAFE OPERATING AREA

DC Tests						
T _C = +25°C, 1 Cycle, t = 1.0 s						
Test						
V _{CE} = 24 Vdc, I _C = 5.8 Adc						
Test 2						
V _{CE} = 45 Vdc, I _C = 0.9 Adc						
Test 3						
V _{CE} = 4.67 Vdc, I _C = 30 Adc						
Test 4						
V _{CE} = 90 Vdc, I _C = 0.19 Adc						2N5671
Test 5						
V _{CE} = 120 Vdc, I _C = 0.11 Adc						2N5672

(3) Pulse Test: Pulse Width = 300μs, Duty Cycle ≤ 2.0%.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.