


Central
Semiconductor Corp.
Central
Semiconductor Corp.
Central
Semiconductor Corp.
**Central™
Semiconductor Corp.**

145 Adams Avenue
Hauppauge, New York 11788



2N5859

NPN SILICON SWITCHING TRANSISTOR

JEDEC TO-39 CASE

DESCRIPTION

The CENTRAL SEMICONDUCTOR 2N5859 is an NPN silicon core driver transistor manufactured by the epitaxial planar process designed for high current and high speed switching applications.

MAXIMUM RATINGS ($T_A=25^\circ\text{C}$ unless otherwise noted)

	SYMBOL		UNIT
Collector-Base Voltage	V_{CB0}	80	V
Collector-Emitter Voltage	V_{CE0}	40	V
Emitter-Base Voltage	V_{EB0}	6.0	V
Collector Current	I_C	2.0	A
Power Dissipation	P_D	1.0	W
Power Dissipation ($T_C=25^\circ\text{C}$)	P_D	5.0	W
Operating and Storage			
Junction Temperature	T_J, T_{STG}	-65 to +200	$^\circ\text{C}$
Thermal Resistance	θ_{JA}	175	$^\circ\text{C/W}$
Thermal Resistance	θ_{JC}	35	$^\circ\text{C/W}$

ELECTRICAL CHARACTERISTICS ($T_A=25^\circ\text{C}$ unless otherwise noted)

SYMBOL	TEST CONDITIONS	MIN	MAX	UNIT
I_{CEV}	$V_{CE}=50\text{V}, V_{BE}(\text{OFF})=2.0\text{V}$		0.20	μA
I_{CEV}	$V_{CE}=50\text{V}, V_{BE}(\text{OFF})=2.0\text{V}, T_A=75^\circ\text{C}$		5.0	μA
I_{CBO}	$V_{CB}=50\text{V}$		0.25	μA
I_{CBO}	$V_{CB}=50\text{V}, T_A=75^\circ\text{C}$		5.0	μA
I_{EBO}	$V_{BE}=5.0\text{V}$		0.10	μA
BV_{CBO}	$I_C=100\mu\text{A}$	80		V
BV_{CEO}	$I_C=10\text{mA}$	40		V
BV_{EBO}	$I_E=10\mu\text{A}$	6.0		V
$V_{CE}(\text{SAT})$	$I_C=500\text{mA}, I_B=50\text{mA}$		0.40	V
$V_{CE}(\text{SAT})$	$I_C=1.0\text{A}, I_B=100\text{mA}$		0.70	V
$V_{BE}(\text{SAT})$	$I_C=500\text{mA}, I_B=50\text{mA}$	0.8	1.0	V
$V_{BE}(\text{SAT})$	$I_C=1.0\text{A}, I_B=100\text{mA}$	0.9	1.25	V
h_{FE}	$V_{CE}=1.0\text{V}, I_C=500\text{mA}$	30	120	
h_{FE}	$V_{CE}=1.0\text{V}, I_C=1.0\text{A}$	15	100	
h_{FE}	$V_{CE}=1.0\text{V}, I_C=1.0\text{A}, T_A=-55^\circ\text{C}$	10	-	
f_T	$V_{CE}=10\text{V}, I_C=50\text{mA}, f=100\text{MHz}$	250	-	MHz
C_{ob}	$V_{CB}=10\text{V}, I_E=0, f=100\text{kHz}$	-	7.0	pF
C_{ib}	$V_{EB}=0.5\text{V}, I_C=0, f=100\text{kHz}$	-	60	pF
t_{ON}	$V_{CC}=30\text{V}, V_{BE}(\text{OFF})=2.0\text{V}, I_C=1.0\text{A}, I_{B1}=100\text{mA}$		35	ns
t_r	$V_{CC}=30\text{V}, V_{BE}(\text{OFF})=2.0\text{V}, I_C=1.0\text{A}, I_{B1}=100\text{mA}$		30	ns
t_d	$V_{CC}=30\text{V}, V_{BE}(\text{OFF})=2.0\text{V}, I_C=1.0\text{A}, I_{B1}=100\text{mA}$		6.0	ns
t_{OFF}	$V_{CC}=30\text{V}, I_C=1.0\text{A}, I_{B1}=I_{B2}=100\text{mA}$		60	ns
t_s	$V_{CC}=30\text{V}, I_C=1.0\text{A}, I_{B1}=I_{B2}=100\text{mA}$		35	ns
t_f	$V_{CC}=30\text{V}, I_C=1.0\text{A}, I_{B1}=I_{B2}=100\text{mA}$		35	ns



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.