




Rectifiers, General Purpose

(Continued)

I_O (AMPS)	3.0			5.0	6.0
@ T_A (°C)	75	100	75	75	60
I_{FSM} (AMPS)	125	200	200	200	400
CASE	 GPR-3A	 DO-201AD		 CASE 106	
V_{RRM} (VOLTS)					
50		CR3-005	CR3-005GPP*		
100	CPR3-010	CR3-010	CR3-010GPP*	CR5-010	
200	CPR3-020	CR3-020	CR3-020GPP*	CR5-020	CR6A2GPP*
400	CPR3-040	CR3-040	CR3-040GPP*	CR5-040	CR6A4GPP*
600	CPR3-060	CR3-060	CR3-060GPP*	CR5-060	CR6A6GPP*
800	CPR3-080	CR3-080	CR3-080GPP*	CR5-080	CR6A8GPP*
1000	CPR3-100	CR3-100	CR3-100GPP*	CR5-100	CR6A10GPP*
1200		CR3-120			

V_F MAX @ $I_F=I_O$	1.1V	1.1V	1.1V	1.2V	1.0V
-----------------------	------	------	------	------	------

I_R MAX @ V_{RRM}	5.0 μ A	10 μ A	5.0 μ A	5.0 μ A	10 μ A
-----------------------	-------------	------------	-------------	-------------	------------

* Device utilizes glass pasivated chip for high reliability.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.