

N-CHANNEL J-FET DEPLETION MODE

Qualified per MIL-PRF-19500/375

Devices

2N3821

2N3822

2N3823


Qualified Level

JANTX
JANTXV

MAXIMUM RATINGS

Parameters / Test Conditions	Symbol	2N3821 2N3822	2N3823	Unit
Gate-Source Voltage	V_{GSR}	50	30	V
Drain-Source Voltage	V_{DS}	50	30	V
Drain-Gate Voltage	V_{DG}	50	30	V
Gate Current	I_{GF}	10		mA
Power Dissipation	P_T	300		mW
Operating Junction & Storage Temperature Range	T_j, T_{stg}	-55 to +200		$^{\circ}C$

(1) Derate linearly 1.7 mW/ $^{\circ}C$ for $T_A = +25^{\circ}C$.



*See appendix A for package outline

ELECTRICAL CHARACTERISTICS ($T_A = 25^{\circ}C$ unless otherwise noted)

Parameters / Test Conditions	Symbol	Min.	Max.	Units
Gate-Source Breakdown Voltage $V_{DS} = 0, I_G = 1.0 \mu A$	$V_{(BR)GSSR}$	50	30	Vdc
Gate Reverse Current $V_{DS} = 0, V_{GS} = 30 Vdc$ $V_{DS} = 0, V_{GS} = 20 Vdc$	I_{GSSR}		0.1 0.5	ηA
Zero-Gate-Voltage Drain Current $V_{GS} = 0, V_{DS} = 15 Vdc$	I_{DSS}	0.5	2.5	mA
Gate-Source Voltage $V_{DS} = 15 Vdc, I_D = 50 \mu A$ $V_{DS} = 15 Vdc, I_D = 200 \mu A$ $V_{DS} = 15 Vdc, I_D = 400 \mu A$	V_{GS}	0.5	2.0	Vdc
Gate-Source Cutoff Voltage $V_{DS} = 15 Vdc, I_D = 0.5 \eta A$	$V_{GS(off)}$		4.0	Vdc

2N3821, 2N3822, 2N3823 JAN SERIES

Parameters / Test Conditions	Symbol	Min.	Max.	Units
Small-Signal Common Source, Short-Circuit Forward Transfer Admittance $V_{GS} = 0, V_{DS} = 15 \text{ Vdc}, f = 1.0 \text{ kHz}$ 2N3821 2N3822 2N3823	$ y_{fs} ^1$	1500 3000 3500	4500 6500 6500	μS
Small-Signal Common Source, Short-Circuit Output Admittance $V_{GS} = 0, V_{DS} = 15 \text{ Vdc}, f = 1.0 \text{ kHz}$ 2N3821 2N3822 2N3823	$ y_{os} $		10 20 35	μS
Small-Signal, Common-Source Short-Circuit Input Capacitance $V_{GS} = 0, V_{DS} = 15 \text{ Vdc}, 100 \text{ kHz} \leq f \leq 1.0 \text{ MHz}$	C_{iss}		6.0	pF
Small-Signal, Common-Source Reverse Transfer Capacitance $V_{DS} = 15 \text{ Vdc}, V_{GS} = 0, 100 \text{ kHz} \leq f \leq 1.0 \text{ MHz}$ 2N3821, 2N3822 2N3823	C_{rss}		3.0 2.0	pF
Small-Signal Common Source, Short-Circuit Forward Transfer Admittance $V_{GS} = 0, V_{DS} = 15 \text{ Vdc}, f = 100 \text{ MHz}$ 2N3821 $f = 100 \text{ MHz}$ 2N3822 $f = 200 \text{ MHz}$ 2N3823	$ y_{fs} ^2$	1500 3000 3200		μS
Small-Signal, Common-Source Short-Circuit Input Conductance $V_{GS} = 0, V_{DS} = 15 \text{ Vdc}, f = 200 \text{ MHz}$ 2N3823 (only)	g_{is}		800	μS
Small-Signal, Common-Source Short-Circuit Output Conductance $V_{GS} = 0, V_{DS} = 15 \text{ Vdc}, f = 200 \text{ MHz}$ 2N3823 (only)	g_{os}		200	μS
Common Source Spot Noise Figure $V_{GS} = 0, V_{DS} = 15 \text{ Vdc}, R_G = 1\text{M}\Omega$ $f = 10 \text{ Hz}$ 2N3821, 2N3822 $f = 1.0 \text{ kHz}$ 2N3821, 2N3822, 2N3823	NF^1		5.0 2.0	dB
Common Source Spot Noise Figure $V_{GS} = 0, V_{DS} = 15 \text{ Vdc}, R_G = 1\text{k}\Omega$ $f = 105 \text{ MHz}$ 2N3823 (only)	NF^2		2.5	dB



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.