

NPN SILICON PLANAR MEDIUM POWER DARLINGTON TRANSISTOR

FXT605

ISSUE 1 – SEPT 93


FEATURES

- * 120 Volt V_{CE0}
- * Gain of 2K at $I_C=1$ Amp
- * $P_{tot}=1$ Watt

APPLICATIONS

- * Lamp, solenoid and relay drivers
- * Replacement of TO126 and TO220 packages

REFER TO ZTX605 FOR GRAPHS



E-Line
TO92 Compatible

ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	V_{CBO}	140	V
Collector-Emitter Voltage	V_{CEO}	120	V
Emitter-Base Voltage	V_{EBO}	10	V
Peak Pulse Current	I_{CM}	4	A
Continuous Collector Current	I_C	1	A
Power Dissipation at $T_{amb} = 25^\circ\text{C}$	P_{tot}	1	W
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +200	$^\circ\text{C}$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^\circ\text{C}$ unless otherwise stated).

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	CONDITIONS.
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	140			V	$I_C=100\mu\text{A}$, $I_E=0$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	120			V	$I_C=10\text{mA}$, $I_B=0^*$
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	10			V	$I_E=100\mu\text{A}$, $I_C=0$
Collector Cut-Off Current	I_{CBO}			0.01 10	μA μA	$V_{CB}=120\text{V}$, $I_E=0$ $V_{CB}=120\text{V}$, $T_{amb}=100^\circ\text{C}$
Emitter Cut-Off Current	I_{EBO}			0.1	μA	$V_{EB}=8\text{V}$, $I_C=0$
Collector-Emitter Cut-Off Current	I_{CES}			10	μA	$V_{CES}=120\text{V}$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$			1.0 1.5	V V	$I_C=0.25\text{A}$, $I_B=0.25\text{mA}^*$ $I_C=1\text{A}$, $I_B=1\text{mA}^*$
Base-Emitter Saturation Voltage	$V_{BE(sat)}$			1.8	V	$I_C=1\text{A}$, $I_B=1\text{mA}^*$
Base-Emitter Turn-On Voltage	$V_{BE(on)}$			1.7	V	$I_C=1\text{A}$, $V_{CE}=5\text{V}^*$
Static Forward Current Transfer Ratio	h_{FE}	2000 5000 2000 500		100K		$I_C=50\text{mA}$, $V_{CE}=5\text{V}^*$ $I_C=500\text{mA}$, $V_{CE}=5\text{V}^*$ $I_C=1\text{A}$, $V_{CE}=5\text{V}^*$ $I_C=2\text{A}$, $V_{CE}=5\text{V}^*$
Transition Frequency	f_T	150			MHz	$I_C=100\text{mA}$, $V_{CE}=10\text{V}$ $f=20\text{MHz}$

* Measured under pulse conditions. Pulse width=300 μs . Duty cycle $\leq 2\%$



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.