

2N 5307 & 2N 5308


NPN DARLINGTON AMP'IFIER

GENERAL DESCRIPTION :

The 2N 5307 & 2N 5308 are NPN silicon planar epitaxial Darlington amplifiers. The devices are suitable for preamplifier input stages requiring high input impedance or very high gain low level amplifier.

MECHANICAL OUTLINE

TO-92B



ECB

ABSOLUTE MAXIMUM RATINGS:

Total Power Dissipation @ $T_A \leq 25^\circ\text{C}$, P_t	400mW
Collector Junction Temperature, T_j	150°C
Storage Temperature Range, T_{stg}	-65°C to +150°C
Soldering Temperature (10 sec. time limit)	260°C
Continuous Collector Current, I_C	300mA
Continuous Base Current, I_B	50mA
Collector to Base Voltage, V_{CB0}	40V
Collector to Emitter Voltage, V_{CE0}	40V
Emitter to Base Voltage, V_{EB0}	12V

ELECTRICAL CHARACTERISTICS @ $T_A=25^\circ\text{C}$ (unless otherwise stated) :

PARAMETER	SYMBOL	MIN	TYP	MAX	UNIT	TEST CONDITIONS
Collector-Emitter Breakdown Voltage	V_{CE0}	40			V	$I_C=10\text{mA}$ $I_B=0$
Collector Cutoff Current	I_{CB0}			100	nA	$V_{CB}=40\text{V}$ $I_E=0$
Emitter Cutoff Current	I_{EB0}			100	nA	$V_{EB}=12\text{V}$ $I_C=0$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$			1.4	V	$I_C=200\text{mA}$ $I_B=0.2\text{mA}$
Base-Emitter Saturation Voltage	$V_{BE(sat)}$			1.6	V	$I_C=200\text{mA}$ $I_B=0.2\text{mA}$
Base-Emitter Voltage	V_{BE}			1.5	V	$V_{CE}=5\text{V}$ $I_C=200\text{mA}$
D.C. Current Gain	h_{FE}	2000		20000		$V_{CE}=5\text{V}$ $I_C=2\text{mA}$

MICRO ELECTRONICS LTD.

38 HUNG TO ROAD, KWUN TONG, HONG KONG. TELEX 43510
 KWUN TONG P. O. BOX 69477 CABLE ADDRESS "MICROTRON"
 TELEPHONE: 3-430181-6 3-893363, 3-892423

FAX: 3-410321

CONTINUE 2

PARAMETER		SYMBOL	MIN	TYP	MAX	UNIT	TEST CONDITIONS
D.C. Current Gain	2N 5307	h_{FE}	6000				$V_{CE}=5V$ $I_C=100mA$
D.C. Current Gain	2N 5308	h_{FE}	7000		70000		$V_{CE}=5V$ $I_C=2mA$
D.C. Current Gain	2N 5308	h_{FE}	20000				$V_{CE}=5V$ $I_C=100mA$
Transition Frequency		f_T	60			MHz	$V_{CE}=5V$ $I_C=2mA$ $f=20MHz$
Collector-Base Capacitance		C_{cb}			10	pF	$V_{CB}=10V$ $I_E=0$ $f=1MHz$
Emitter-Base Capacitance		C_{eb}		10.5		pF	$V_{EB}=0.5V$ $I_C=0$ $f=1MHz$
Small Signal Current Gain	2N 5307	h_{fe}	2000				$V_{CE}=5V$ $I_C=2mA$ $f=1KHz$
Small Signal Current Gain	2N 5308	h_{fe}	7000				$V_{CE}=5V$ $I_C=2mA$ $f=1KHz$
Input Impedance		h_{ie}		650		Kohm	$V_{CE}=5V$ $I_C=2mA$ $f=1KHz$

3-5-1977.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.