

MICRO ELECTRONICS

BC143

GENERAL DESCRIPTION :

The BC143 is a PNP silicon planar epitaxial transistor. It features low saturation voltage, low collector cutoff current and high breakdown voltage. It is intended for use in driver stage of high power audio amplifiers. It can be supplied together with BC144 as a matched pair.

MECHANICAL OUTLINE



ABSOLUTE MAXIMUM RATINGS :

Continuous Power Dissipation @ $T_A=25^\circ\text{C}$, P_{max}	0.8W
Continuous Power Dissipation @ $T_A=45^\circ\text{C}$, P_{max}	0.708W
Continuous Power Dissipation @ $T_C=25^\circ\text{C}$, P_{max}	4W
Continuous Power Dissipation @ $T_C=75^\circ\text{C}$, P_{max}	2.86W
Maximum Collector Junction Temperature, T_j	200°C
Storage Temperature Range, T_{stg}	-55°C to +200°C
Soldering Temperature (10 sec. time limit)	260°C
Continuous Collector Current, I_C max	-1A
Collector-Base Voltage, V_{CBO}	-60V
Collector-Emitter Voltage, V_{CEO}	-60V
Emitter-Base Voltage, V_{EBO}	-5V

ELECTRICAL CHARACTERISTICS @ $T_A=25^\circ\text{C}$ (unless otherwise stated) :

PARAMETER	SYMBOL	MIN	TYP	MAX	UNIT	TEST CONDITIONS
Collector-Base Breakdown Voltage	BV_{CBO}	-60			V	$I_C=-10\mu\text{A}$ $I_E=0$
Collector-Emitter Breakdown Voltage	LV_{CEO}	-60			V	$I_C=-10\text{mA}$ $I_B=0$
Emitter-Base Breakdown Voltage	BV_{EBO}	-5			V	$I_E=-10\mu\text{A}$ $I_C=0$
Collector Cutoff Current	I_{CBO}		-0.1	-50	nA	$V_{\text{CB}}=-30\text{V}$ $I_E=0$
Collector Cutoff Current	I_{CBO}		-0.002	-50	μA	$V_{\text{CB}}=-30\text{V}$ $I_E=0$ $T_A=75^\circ\text{C}$
Collector-Emitter Saturation Voltage	$V_{\text{CE}}(\text{sat})$		-0.3		V	$I_C=-500\text{mA}$ $I_B=-25\text{mA}$
Collector-Emitter Saturation Voltage	$V_{\text{CE}}(\text{sat})$		-0.25	-0.5	V	$I_C=-500\text{mA}$ $I_B=-50\text{mA}$
Collector-Emitter Saturation Voltage	$V_{\text{CE}}(\text{sat})$		-1.2		V	$I_C=-1000\text{mA}$ $I_B=-50\text{mA}$
Collector-Emitter Saturation Voltage	$V_{\text{CE}}(\text{sat})$		-0.7	-1	V	$I_C=-1000\text{mA}$ $I_B=-100\text{mA}$
Base-Emitter On Voltage	$V_{\text{BE}}(\text{on})$		-0.7		V	$V_{\text{CE}}=-10\text{V}$ $I_C=-10\text{mA}$
Base-Emitter On Voltage	$V_{\text{BE}}(\text{on})$		-0.75		V	$V_{\text{CE}}=-10\text{V}$ $I_C=-100\text{mA}$
Base-Emitter On Voltage	$V_{\text{BE}}(\text{on})$		-0.85		V	$V_{\text{CE}}=-1\text{V}$ $I_C=-300\text{mA}$
Base-Emitter On Voltage	$V_{\text{BE}}(\text{on})$		-0.93		V	$V_{\text{CE}}=-1\text{V}$ $I_C=-500\text{mA}$

MICRO ELECTRONICS LTD. 美科有限公司

38, Hung To Road, Microtron Building, Kwun Tong, Kowloon, Hong Kong.
Kwun Tong P.O. Box 69477 Hong Kong. Fax No. 341 0321 Telex: 43510 Micro Hx. Tel: 343 0181-5

P.T.O.

----- CONTINUE -----

ELECTRICAL CHARACTERISTICS @ $T_A=25^{\circ}\text{C}$ (unless otherwise stated) :

PARAMETER	SYMBOL	MIN	TYP	MAX	UNIT	TEST CONDITIONS
D.C. Current Gain	h_{FE}		88			$V_{CE}=-10\text{V}$ $I_C=-10\text{mA}$
D.C. Current Gain	h_{FE}		85			$V_{CE}=-10\text{V}$ $I_C=-10\text{mA}$
D.C. Current Gain	h_{FE}	20	40			$V_{CE}=-1\text{V}$ $I_C=-300\text{mA}$
D.C. Current Gain	h_{FE}	15	30			$V_{CE}=-1\text{V}$ $I_C=-500\text{mA}$
High Frequency Current Gain	h_{fe}		1.5			$V_{CE}=-10\text{V}$ $I_C=-50\text{mA}$ $f=100\text{MHz}$
Collector-Base Capacitance	C_{ob}		13		pF	$V_{CB}=-10\text{V}$ $I_E=0$
BC143-BC144 match pair	h_{FE} ratio	0.8		1.25		$V_{CE}=-1\text{V}$ $I_C=-50\text{mA}$



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.