

BIPOLAR TRANSISTORS

Ratings and Specifications

COLLMER SEMICONDUCTOR INC 48E D ■ 2238792 0001613 088 ■ COL

T-33-35

34 1200 volts class power transistor modules

- Power transistors and free wheels are built into one package.
- All terminals are insulated from mounting plate.
- Best suited for motor control applications with 440 to 480 V AC inputs and power supplies.
- Terminal layout in which drive wiring and power wiring do not come across.

Device type	V _{CB0}	V _{CE0}	V _{CEX} (sus)	I _c cont.	P _c	h _{FE} min.	I _c	V _{CE}	Switching time (Max.)			Package	Net weight Grams	Equivalent circuit Page 41
	Volts	Volts	Volts	Amps.	Watts		Amps.	Volts	t _{on} μsec.	t _{stg} μsec.	t _r μsec.			
2DI30A-120	1200	1200	1200	30	300	70	30	5	3	15	3	M204	175	Fig. E1
2DI50A-120	1200	1200	1200	50	400	70	50	5	3	15	3	M206	265	Fig. E1
2DI75A-120	1200	1200	1200	75	500	70	75	5	3	15	3	M206	265	Fig. E1
2DI100A-120	1200	1200	1200	100	800	70	100	5	3	15	3	M207	550	Fig. E2
2DI150A-120	1200	1200	1200	150	1000	70	150	5	3	15	3	M207	550	Fig. E2
1DI200A-120	1200	1200	1200	200	1400	70	200	5	2.5	15	3	M105	560	Fig. D1
1DI300A-120	1200	1200	1200	300	2000	70	300	5	3	15	3	M105	560	Fig. D1
1DI400A-120	1200	1200	1200	400	3120	100	400	5	3	15	3	M107	830	Fig. D1

35 1400 volts class power transistor modules

- Power transistors and free wheels are built into one package.
- Terminal layout in which drive wiring and power wiring do not come across.

Device type	V _{CB0}	V _{CE0}	V _{CEX} (sus)	I _c cont.	P _c	h _{FE} min.	I _c	V _{CE}	Switching time (Max.)			Package	Net weight Grams	Equivalent circuit Page 41
	Volts	Volts	Volts	Amps.	Watts		Amps.	Volts	t _{on} μsec.	t _{stg} μsec.	t _r μsec.			
2DI30A-140	1400	1400	1200	30	300	70	30	5	3	15	3	M204	175	Fig. E1
2DI50A-140	1400	1400	1200	50	400	70	50	5	3	15	3	M206	265	Fig. E1
2DI75A-140	1400	1400	1200	75	500	70	75	5	3	15	3	M206	265	Fig. E1
2DI100A-140	1400	1400	1200	100	800	70	100	5	3	15	3	M207	550	Fig. E2
2DI150A-140	1400	1400	1200	150	1000	70	150	5	3	15	3	M207	550	Fig. E2
1DI200A-140	1400	1400	1200	200	1400	70	200	5	3	15	3	M105	560	Fig. D1
1DI300A-140	1400	1400	1200	300	2000	70	300	5	3	15	3	M105	560	Fig. D1

36 4-pack power transistor modules

- 4 power transistors and 4 free wheels are built into one package.
- All terminals are insulated from mounting plate.
- Ideally suited for 15 to 20 Ampere H-bridge circuits.

Device type	V _{CB0}	V _{CE0}	V _{CE0} (sus)	I _c cont.	P _c	h _{FE} min.	I _c	V _{CE}	Switching time (Max.)			Package	Net weight Grams	Equivalent circuit Page 44
	Volts	Volts	Volts	Amps.	Watts		Amps.	Volts	t _{on} μsec.	t _{stg} μsec.	t _r μsec.			
EVF31H-035	500	500	350	20	80	50	10	5	0.8	2.5	1.0	M401	180	Fig. L1
EVF31H-050	600	600	450	15	100	100	15	5	1.5	12.0	2.5	M401	180	Fig. L1

This datasheet has been downloaded from:

www.DatasheetCatalog.com

Datasheets for electronic components.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.