

ELECTRICAL CHARACTERISTICS ($T_A = 25^\circ\text{C}$ unless otherwise stated)

Parameter	Test Conditions	Min.	Typ.	Max.	Unit
$V_{CEO(sus)}$ Collector – Emitter Sustaining Voltage	$I_C = 10\text{mA}$ $I_B = 0$	200			V
$V_{CER(sus)}$ Collector – Emitter Sustaining Voltage	$I_C = 10\text{mA}$ $R_{EB} = 100\Omega$	250			
I_{CES} Collector – Emitter Cut-off Current	$V_{CE} = 200\text{V}$ $I_B = 0$			1.0	μA
	$V_{CE} = 175$ $T_C = 150^\circ\text{C}$			100	
I_{EBO} Emitter Base Cut-off Current	$V_{EB} = 6\text{V}$ $I_E = 0$			10	μA
$V_{CE(sat)}$ Collector – Emitter Saturation Voltage	$I_C = 3.0\text{A}$ $I_B = 0.3\text{A}$			0.4	V
$V_{BE(sat)}$ Base – Emitter On Voltage	$I_C = 3.0\text{A}$ $I_B = 0.3\text{A}$			1.2	
h_{FE} DC Current Gain	$I_C = 0.5\text{mA}$ $V_{CE} = 2\text{V}$	40			—
	$I_C = 1.0\text{A}$ $V_{CE} = 5\text{V}$	40		120	
	$I_C = 3.0\text{A}$ $V_{CE} = 5\text{V}$	15			
C_{obo} Output Capacitance	$V_{CB} = 5.0\text{V}$ $f = 1\text{MHz}$			125	pF
$[h_{fe}]$ Small Signal Current Gain	$V_{CE} = 5.0\text{V}$ $I_C = 0.5\text{A}$ $f = 10\text{MHz}$	2.0			—
t_{on} Turn on time	$I_C = 1.0\text{A}$ $V_{CC} = 100\text{V}$ $I_{B1} = - I_{B2} = 30\text{mA}$			0.25	μsec
t_{off} Turn off time	$I_C = 1.0\text{A}$ $V_{CC} = 100\text{V}$ $I_{B1} = - I_{B2} = 30\text{mA}$			1.5	μA

1) f_t is defined as the frequency at which $|h_{fe}|$ extrapolates to unity.

Semelab plc. Telephone +44(0)1455 556565. Fax +44(0)1455 552612.

E-mail: sales@semelab.co.uk Website: <http://www.semelab.co.uk>



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.