

SOT223 PNP SILICON PLANAR HIGH VOLTAGE TRANSISTOR

BF721

ISSUE 4 – MARCH 2001



FEATURES


- * High breakdown and low saturation voltages

APPLICATIONS

- * Suitable for video output stages in TV sets
- * Switching power supplies

COMPLEMENTARY TYPE:- BF720

PARTMARKING DETAILS:- BF721



ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	V_{CBO}	-300	V
Collector-Emitter Voltage	V_{CEO}	-300	V
Emitter-Base Voltage	V_{EBO}	-5	V
Peak Pulse Current	I_{CM}	-100	mA
Continuous Collector Current	I_C	-50	mA
Power Dissipation at $T_{amb}=25^{\circ}C$	P_{tot}	-2	W
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150	$^{\circ}C$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$ unless otherwise stated).

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	CONDITIONS.
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	-300			V	$I_C = -10\mu A, I_E = 0$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	-300			V	$I_C = -1mA, I_B = 0^*$
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	-5			V	$I_E = -100\mu A, I_C = 0$
Collector Cut-Off Current	I_{CBO}			-10	nA	$V_{CB} = -200V, I_E = 0$ †
Collector Cut-Off Current	I_{CER}			-50 -10	nA μA	$V_{CE} = -200V, R_{BE} = 2.7K\Omega$ $V_{CE} = -200V, R_{BE} = 2.7K\Omega$ †
Emitter Cut-Off Current	I_{EBO}			-10	μA	$V_{EB} = -5V, I_C = 0$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$			-0.6	V	$I_C = -30mA, I_B = -5mA^*$
Base Emitter Saturation Voltage	$V_{BE(sat)}$			-0.9	V	$I_C = -20mA, I_B = -2mA^*$
Static Forward Current Transfer Ratio	h_{FE}	-50				$I_C = -25mA, V_{CE} = -20V^*$
Transition Frequency	f_T		100		MHz	$I_C = -10mA, V_{CE} = -10V$ $f = 100MHz$
Output Capacitance	C_{obo}		0.8		pF	$V_{CB} = -30V, f = 1MHz$

† $T_{amb} = 150^{\circ}C$

*Measured under pulsed conditions.

For typical characteristics graphs see FMMTA92 datasheet.





LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.