


# PNP SILICON PLANAR MEDIUM POWER TRANSISTOR

## 2N6732

ISSUE 1 – MARCH 94

### FEATURES

- \* 80 Volt  $V_{CEO}$
- \* Gain of 100 at  $I_C = 350$  mA
- \*  $P_{tot} = 1$  Watt



E-Line  
TO92 Compatible

### ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	$V_{CBO}$	-100	V
Collector-Emitter Voltage	$V_{CEO}$	-80	V
Emitter-Base Voltage	$V_{EBO}$	-5	V
Peak Pulse Current	$I_{CM}$	-2	A
Continuous Collector Current	$I_C$	-1	A
Power Dissipation at $T_{amb} = 25^\circ\text{C}$	$P_{tot}$	1	W
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +200	$^\circ\text{C}$

### ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^\circ\text{C}$ unless otherwise stated).

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	CONDITIONS.
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	-100			V	$I_C = -100\mu\text{A}$ , $I_E = 0$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	-80			V	$I_C = -10\text{mA}$ , $I_B = 0^*$
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	-5			V	$I_E = -1\text{mA}$ , $I_C = 0$
Collector Cut-Off Current	$I_{CBO}$			-0.1	$\mu\text{A}$	$V_{CB} = -80\text{V}$ , $I_E = 0$
Emitter Cut-Off Current	$I_{EBO}$			-10	$\mu\text{A}$	$V_{EB} = -5\text{V}$ , $I_C = 0$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$			-0.35	V	$I_C = -350\text{mA}$ , $I_B = -35\text{mA}^*$
Base-Emitter Turn-On Voltage	$V_{BE(on)}$			-1.0	V	$I_C = -350\text{mA}$ , $V_{CE} = -2\text{V}^*$
Static Forward Current Transfer Ratio	$h_{FE}$	100 100		300		$I_C = -10\text{mA}$ , $V_{CE} = -2\text{V}^*$ $I_C = -350\text{mA}$ , $V_{CE} = -2\text{V}^*$
Transition Frequency	$f_T$	50		500	MHz	$I_C = -200\text{mA}$ , $V_{CE} = -5\text{V}$ $f = 20\text{MHz}$
Collector-Base Capacitance	$C_{CB}$			20	pF	$V_{CB} = -10\text{V}$ , $f = 1\text{MHz}$

\*Measured under pulsed conditions. Pulse width=300 $\mu\text{s}$ . Duty cycle  $\leq 2\%$



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.