

Switching diode

DA221M / DA221 / DA204U / DA204K DA228U / DA228K / UMR12N

●Applications

Bias circuits
Protection circuits


●Features

- 1) Three types of packages are available.
(VMD3, EMD3, UMD3, SMD3)
- 2) Two diode elements are connected in series
($V_F \times 2$) per circuit.


●Construction

Silicon epitaxial planar

●Circuit



●External dimensions (Unit : mm)



DA221M/DA221/DA204U/DA204K/DA228U/DA228K/UMR12N

Diodes

●Marking

VMD3		EMD3		UMD3		UMD6		SMD3	
DA221M		DA221		DA204U		UMR12N		DA204K	
-	-	-	-	DA228U		-	-	DA228K	

●Absolute maximum ratings (Ta=25°C)

Type	Peak reverse voltage V _{RM} (V)	DC reverse voltage V _R (V)	Peak forward current I _{FM} (mA)	Mean rectifying current I _o (mA)	Surge current (1μs) I _{surge} (mA)	Power dissipation (TOTAL) Pd(mW)	Junction temperature T _j (°C)	Storage temperature T _{stg} (°C)
DA221M	20	20	200	100	300	150	150	-55 to +150
DA221	20	20	200	100	300	150	150	-55 to +150
DA204U	20	20	200	100	300	200	150	-55 to +150
DA228U	80	80	200	100	300	200	150	-55 to +150
DA204K	20	20	200	100	300	200	150	-55 to +150
DA228K	80	80	200	100	300	200	150	-55 to +150
UMR12N	80	80	200	100	300	200	150	-55 to +150

●Electrical characteristics (Ta=25°C)

Type	Forward voltage		Reverse current		Fig.
	V _F (V) Max.	Cond. I _F (mA)	I _R (μA) Max.	Cond. V _R (V)	
DA221M	1.0	10	0.1	15	1 to 4
DA221	1.0	10	0.1	15	1 to 4
DA204U	1.0	10	0.1	15	1 to 4
DA228U	1.2	100	0.1	80	5 to 9
DA204K	1.0	10	0.1	15	1 to 4
DA228K	1.2	100	0.1	80	5 to 9
UMR12N	1.2	100	0.1	80	5 to 9

DA221M/DA221/DA204U/DA204K/DA228U/DA228K/UMR12N

Diodes

●Electrical characteristic curves (Ta=25°C)

(DA221, DA204U, DA204K) ...Fig.1 to 4




Fig.1 Forward characteristics




Fig.2 Forward characteristics




Fig.3 Reverse characteristics




Fig.4 Capacitance between terminals characteristics

DA221M/DA221/DA204U/DA204K/DA228U/DA228K/UMR12N

Diodes

(DA228U, DA228K, UMR12N) ...Fig.5 to 9




Fig.5 Forward characteristics




Fig.6 Forward characteristics




Fig.7 Reverse characteristics




Fig.8 Reverse characteristics




Fig.9 Capacitance between terminals characteristics

Notes

- No technical content pages of this document may be reproduced in any form or transmitted by any means without prior permission of ROHM CO.,LTD.
- The contents described herein are subject to change without notice. The specifications for the product described in this document are for reference only. Upon actual use, therefore, please request that specifications to be separately delivered.
- Application circuit diagrams and circuit constants contained herein are shown as examples of standard use and operation. Please pay careful attention to the peripheral conditions when designing circuits and deciding upon circuit constants in the set.
- Any data, including, but not limited to application circuit diagrams information, described herein are intended only as illustrations of such devices and not as the specifications for such devices. ROHM CO.,LTD. disclaims any warranty that any use of such devices shall be free from infringement of any third party's intellectual property rights or other proprietary rights, and further, assumes no liability of whatsoever nature in the event of any such infringement, or arising from or connected with or related to the use of such devices.
- Upon the sale of any such devices, other than for buyer's right to use such devices itself, resell or otherwise dispose of the same, no express or implied right or license to practice or commercially exploit any intellectual property rights or other proprietary rights owned or controlled by
- ROHM CO., LTD. is granted to any such buyer.
- Products listed in this document use silicon as a basic material.
Products listed in this document are no antiradiation design.

The products listed in this document are designed to be used with ordinary electronic equipment or devices (such as audio visual equipment, office-automation equipment, communications devices, electrical appliances and electronic toys).

Should you intend to use these products with equipment or devices which require an extremely high level of reliability and the malfunction of which would directly endanger human life (such as medical instruments, transportation equipment, aerospace machinery, nuclear-reactor controllers, fuel controllers and other safety devices), please be sure to consult with our sales representative in advance.

About Export Control Order in Japan

Products described herein are the objects of controlled goods in Annex 1 (Item 16) of Export Trade Control Order in Japan.

In case of export from Japan, please confirm if it applies to "objective" criteria or an "informed" (by MITI clause) on the basis of "catch all controls for Non-Proliferation of Weapons of Mass Destruction.

This datasheet has been downloaded from:

www.DatasheetCatalog.com

Datasheets for electronic components.



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.