

# SOT89 NPN SILICON PLANAR MEDIUM POWER TRANSISTOR

## FCX491

ISSUE 3 - OCTOBER 1995




### FEATURES

- \* 60 Volt  $V_{CEO}$
- \* 1 Amp continuous current
- \*  $P_{tot} = 1$  Watt

COMPLEMENTARY TYPE – FCX591

PARTMARKING DETAIL – N1



### ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	$V_{CBO}$	80	V
Collector-Emitter Voltage	$V_{CEO}$	60	V
Emitter-Base Voltage	$V_{EBO}$	5	V
Continuous Collector Current	$I_C$	1	A
Peak Pulse Current	$I_{CM}$	2	A
Power Dissipation at $T_{amb}=25^{\circ}C$	$P_{tot}$	1	W
Operating and Storage Temperature Range	$T_j; T_{stg}$	-65 to +150	$^{\circ}C$

### ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$ ).

PARAMETER	SYMBOL	MIN.	MAX.	UNIT	CONDITIONS.
Breakdown Voltages	$V_{(BR)CBO}$	80		V	$I_C=100\mu A$
	$V_{CEO(sus)}$	60		V	$I_C=10mA^*$
	$V_{(BR)EBO}$	5		V	$I_E=100\mu A$
Collector Cut-Off Currents	$I_{CBO}$		100	nA	$V_{CB}=60V,$
	$I_{CES}$		100	nA	$V_{CE}=60V$
Emitter Cut-Off Current	$I_{EBO}$		100	nA	$V_{EB}=4V$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$		0.25	V	$I_C=500mA, I_B=50mA^*$
			0.50	V	$I_C=1A, I_B=100mA^*$
Base-Emitter Saturation Voltage	$V_{BE(sat)}$		1.1	V	$I_C=1A, I_B=100mA^*$
Base-Emitter Turn On Voltage	$V_{BE(on)}$		1.0	V	$I_C=1A, V_{CE}=5V^*$
Static Forward Current Transfer Ratio	$h_{FE}$	100	300		$I_C=1mA, V_{CE}=5V$
		100			$I_C=500mA, V_{CE}=5V^*$
		80			$I_C=1A, V_{CE}=5V^*$
		30			$I_C=2A, V_{CE}=5V^*$
Transition Frequency	$f_T$	150		MHz	$I_C=50mA, V_{CE}=10V$ $f=100MHz$
Collector-Base Breakdown Voltage	$C_{obo}$		10	pF	$V_{CB}=10V, f=1MHz$

\*Measured under pulsed conditions. Pulse width=300 $\mu s$ . Duty cycle  $\leq 2\%$   
For typical Characteristics graphs see FMMT491 datasheet



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

**[LittleDiode.com](http://LittleDiode.com)**

Looking forward to providing you with the best possible service.