


SOT223 NPN SILICON PLANAR MEDIUM POWER TRANSISTOR

ISSUE 3 – NOVEMBER 1995

FZT493

COMPLEMENTARY TYPE – FZT593

PARTMARKING DETAIL – FZT493



ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	V_{CBO}	120	V
Collector-Emitter Voltage	V_{CEO}	100	V
Emitter-Base Voltage	V_{EBO}	5	V
Peak Pulse Current	I_{CM}	2	A
Continuous Collector Current	I_C	1	A
Base Current	I_B	200	mA
Power Dissipation at $T_{amb}=25^\circ\text{C}$	P_{tot}	2	W
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150	$^\circ\text{C}$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^\circ\text{C}$).

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	CONDITIONS.
Breakdown Voltages	$V_{(BR)CBO}$	120			V	$I_C=100\mu\text{A}$
	$V_{(BR)CEO}$	100			V	$I_C=10\text{mA}^*$
	$V_{(BR)EBO}$	5			V	$I_E=100\mu\text{A}$
Cut-Off Currents	I_{CBO}			100	nA	$V_{CB}=100\text{V}$
	I_{EBO}			100	nA	$V_{EB}=4\text{V}$
	I_{CES}			100	nA	$V_{CES}=100\text{V}$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$			0.3 0.6	V	$I_C=500\text{mA}, I_B=50\text{mA}^*$ $I_C=1\text{A}, I_B=100\text{mA}^*$
Base-Emitter Saturation Voltage	$V_{BE(sat)}$			1.15	V	$I_C=1\text{A}, I_B=100\text{mA}^*$
Base-Emitter Turn-On Voltage	$V_{BE(on)}$			1.0	V	$I_C=1\text{A}, V_{CE}=10\text{V}^*$
Static Forward Current	h_{FE}	100 100 80 30		300		$I_C=1\text{mA}, V_{CE}=10\text{V}$ $I_C=250\text{mA}, V_{CE}=10\text{V}^*$ $I_C=500\text{mA}, V_{CE}=10\text{V}^*$ $I_C=1\text{A}, V_{CE}=10\text{V}^*$
Transition Frequency	f_T	150			MHz	$I_C=50\text{mA}, V_{CE}=10\text{V}$, $f=100\text{MHz}$
Output Capacitance	C_{obo}			10	pF	$V_{CB}=10\text{V}, f=1\text{MHz}$

*Measured under pulsed conditions. Pulse width=300 μs . Duty cycle $\leq 2\%$
For typical Characteristics graphs see FMMT493 datasheet



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.