

SOT23 N-CHANNEL ENHANCEMENT MODE VERTICAL DMOS FET


BSS123A

ISSUE 4 – APRIL 1998

FEATURES

- * $BV_{DSS} = 100V$
- * Low Threshold

PARTMARKING DETAIL – SAA



ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Drain-Source Voltage	V_{DS}	100	V
Drain-Gate Voltage	V_{DGR}	100	V
Continuous Drain Current at $T_{amb}=25^{\circ}C$	I_D	170	mA
Pulsed Drain Current	I_{DM}	680	mA
Gate-Source Voltage	V_{GS}	± 20	V
Power Dissipation at $T_{amb}=25^{\circ}C$	P_{tot}	360	mW
Operating and Storage Temperature Range	$T_j:T_{stg}$	-55 to +150	$^{\circ}C$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$ unless otherwise stated).

PARAMETER	SYMBOL	MIN.	TYP.	MAX.	UNIT	CONDITIONS.
Drain-Source Breakdown Voltage	BV_{DSS}	100			V	$I_D=0.25mA, V_{GS}=0V$
Gate-Source Threshold Voltage	$V_{GS(th)}$	0.5		2.0	V	$I_D=1mA, V_{DS}=V_{GS}$
Gate-Body Leakage	I_{GSS}			50	nA	$V_{GS}=\pm 20V, V_{DS}=0V$
Zero Gate Voltage Drain Current	I_{DSS}			500	nA	$V_{DS}=100V, V_{GS}=0V$
Static Drain-Source On-State Resistance (1)	$R_{DS(on)}$			6 10	Ω Ω	$V_{GS}=10V, I_D=170mA$ $V_{GS}=4.5V, I_D=170mA$
Forward Transconductance(1)(2)	g_{fs}	80			mS	$V_{DS}=25V, I_D=100mA$
Input Capacitance (2)	C_{iss}		25		pF	$V_{DS}=25V, V_{GS}=0V, f=1MHz$
Common Source Output Capacitance (2)	C_{oss}		9		pF	
Reverse Transfer Capacitance (2)	C_{rss}		4		pF	
Turn-On Delay Time (2)(3)	$t_{d(on)}$		10		ns	$V_{DD}=30V, I_D=280mA$
Rise Time (2)(3)	t_r		10		ns	
Turn-Off Delay Time (2)(3)	$t_{d(off)}$		15		ns	
Fall Time (2)(3)	t_f		25		ns	

(1) Measured under pulsed conditions. Width=300 μ s. Duty cycle $\leq 2\%$ (2) Sample test.

(3) Switching times measured with 50 Ω source impedance and <5ns rise time on a pulse generator



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.