


# SOT23 NPN SILICON PLANAR DARLINGTON TRANSISTORS

**FMMTA12**  
**FMMTA13**  
**FMMTA14**

## ISSUE 4 - DECEMBER 1996

COMPLEMENTARY TYPES - FMMTA12 - NONE  
FMMTA13 - FMMTA63  
FMMTA14 - FMMTA64

PARTMARKING DETAILS - FMMTA12 - 3W  
FMMTA13 - 1M  
FMMTA14 - 1N



## ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	FMMTA12	FMMTA13/14	UNIT
Collector-Base Voltage	$V_{CBO}$		40	V
Collector-Emitter Voltage	$V_{CEO}$		40	V
Collector-Emitter Voltage	$V_{CES}$	20	40	V
Emitter-Base Voltage	$V_{EBO}$		10	V
Continuous Collector Current	$I_C$		300	mA
Power Dissipation at $T_{amb}=25^{\circ}C$	$P_{tot}$		330	mW
Operating and Storage Temperature Range	$T_j; T_{stg}$		-55 to +150	$^{\circ}C$

## ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$ ).

PARAMETER	SYMBOL	MIN.	MAX.	UNIT	CONDITIONS.
Collector-Emitter Breakdown Voltage	$V_{(BR)CES}$	20 40		V V	$I_C=100\mu A, I_B=0^*$ $I_C=100\mu A, I_B=0^*$
Collector Cut-Off Current	$I_{CES}$		100	nA	$V_{CB}=15V, V_{BE}=0$
Collector Cut-Off Current	$I_{CBO}$		100 100	nA nA	$V_{CB}=15V, I_E=0$ $V_{CB}=30V, I_E=0$
Emitter Cut-Off Current	$I_{EBO}$		100	nA	$V_{EB}=10V, I_C=0$
Static Forward Current Transfer Ratio	$h_{FE}$	20K 5K 10K 10K 20K			$I_C=10mA, V_{CE}=5V^*$ $I_C=10mA, V_{CE}=5V^*$ $I_C=100mA, V_{CE}=5V^*$ $I_C=10mA, V_{CE}=5V^*$ $I_C=100mA, V_{CE}=5V^*$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$		1.0 0.9	V V	$I_C=10mA, I_B=0.01mA$ $I_C=100mA, I_B=0.1mA$
Base-Emitter On Voltage	$V_{BE(on)}$		1.4 2.0	V V	$I_C=10mA, V_{CE}=5V^*$ $I_C=100mA, V_{CE}=5V^*$

\*Measured under pulsed conditions. Pulse width = 300 $\mu s$ . Duty cycle  $\leq 2\%$   
Spice parameter data is available upon request for these devices  
For typical graphs see FMMIT38A datasheet



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.