


SOT23 NPN SILICON PLANAR SWITCHING TRANSISTOR

FMMT4124

ISSUE 2 – MARCH 94



PARTMARKING DETAIL – ZC



ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	VALUE	UNIT
Collector-Base Voltage	V_{CBO}	30	V
Collector-Emitter Voltage	V_{CEO}	25	V
Emitter-Base Voltage	V_{EBO}	5	V
Continuous Collector Current	I_C	200	mA
Power Dissipation at $T_{amb}=25^{\circ}C$	P_{tot}	330	mW
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150	$^{\circ}C$

ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$).

PARAMETER	SYMBOL	MIN.	MAX.	UNIT	CONDITIONS.
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	30		V	$I_C=10\mu A$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	25		V	$I_C=1mA^*$
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	5		V	$I_E=10\mu A$
Collector Cut-Off Current	I_{CBO}		50	nA	$V_{CB}=20V$
Emitter Cut-Off Current	I_{EBO}		50	nA	$V_{EB}=3V$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$		0.3	V	$I_C=50mA, I_B=5mA^*$
Base-Emitter Saturation Voltage	$V_{BE(sat)}$		0.95	V	$I_C=50mA, I_B=5mA^*$
Static Forward Current Transfer Ratio	h_{FE}	120 60	360		$I_C=2mA, V_{CE}=1V^*$ $I_C=50mA, V_{CE}=1V^*$
Transition Frequency	f_T	300		MHz	$I_C=10mA, V_{CE}=20V, f=100MHz$
Output Capacitance	C_{obo}		4	pF	$V_{CB}=5V, I_E=0, f=140KHz$
Input Capacitance	C_{ibo}		8	pF	$V_{BE}=0.5V, I_E=0, f=140KHz$
Noise Figure	N		6	dB	$I_C=200\mu A, V_{CE}=5V, R_g=2k\Omega$ $f=30Hz$ to $15KHz$ at 3dB points
Small Signal Current Transfer	h_{fe}	120	480		$I_C=2mA, V_{CE}=1V, f=1KHz$

SWITCHING CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$).

PARAMETER	SYMBOL	TYP.	UNIT	CONDITIONS
Delay Time	t_d	24	ns	$V_{CC}=3V, V_{BE(off)}=0.5V$ $I_C=10mA, I_{B1}=1mA$
Rise Time	t_r	13	ns	
Storage Time	t_s	125	ns	$V_{CC}=3V, I_C=10mA$ $I_{B1}=I_{B2}=1mA$
Fall Time	t_f	11	ns	

*Measured under pulsed conditions. Pulse width=300 μs . Duty cycle $\leq 2\%$



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

LittleDiode.com

Looking forward to providing you with the best possible service.