


# SOT23 PNP SILICON PLANAR HIGH VOLTAGE TRANSISTORS

## FMMT5400 FMMT5401

ISSUE 4 - NOVEMBER 1996 

PARTMARKING DETAILS - FMMT5400 - 1LZ  
FMMT5401 - Z2L

COMPLEMENTARY TYPES - FMMT5400 - FMMT5550  
FMMT5401 - FMMT5551



### ABSOLUTE MAXIMUM RATINGS.

PARAMETER	SYMBOL	FMMT5400	FMMT5401	UNIT
Collector-Base Voltage	$V_{CBO}$	-130	-160	V
Collector-Emitter Voltage	$V_{CEO}$	-120	-150	V
Emitter-Base Voltage	$V_{EBO}$	-5	-5	V
Continuous Collector Current	$I_C$	-600	-600	mA
Power Dissipation at $T_{amb}=25^{\circ}C$	$P_{tot}$	330	330	mW
Operating and Storage Temperature Range	$T_j; T_{stg}$	-55 to +150		$^{\circ}C$

### ELECTRICAL CHARACTERISTICS (at $T_{amb} = 25^{\circ}C$ ).

PARAMETER	SYMBOL	FMMT5400		FMMT5401		UNIT	CONDITIONS.
		MIN.	MAX.	MIN.	MAX.		
Collector-Base Breakdown Voltage	$V_{(BR)CBO}$	-130		-160		V	$I_C = -100\mu A$
Collector-Emitter Breakdown Voltage	$V_{(BR)CEO}$	-120		-150		V	$I_C = -1mA$
Emitter-Base Breakdown Voltage	$V_{(BR)EBO}$	-5		-5		V	$I_E = -10\mu A$
Collector Cut-Off Current	$I_{CBO}$		-100 -100		-50 -50	nA $\mu A$ nA $\mu A$	$V_{CB} = -100V$ $V_{CB} = -100V, T_A = 100^{\circ}C$ $V_{CB} = -120V$ $V_{CB} = -120V, T_A = 100^{\circ}C$
Static Forward Current Transfer Ratio	$h_{FE}$	30 40 40	-180	50 60 50	240		$I_C = -1mA, V_{CE} = -5V$ $I_C = -10mA, V_{CE} = -5V$ $I_C = -50mA, V_{CE} = -5V$
Collector-Emitter Saturation Voltage	$V_{CE(sat)}$		-0.2 -0.5		-0.2 -0.5	V V	$I_C = -10mA, I_B = -1mA$ $I_C = -50mA, I_B = -5mA$
Base-Emitter Saturation Voltage	$V_{BE(sat)}$		-1.0 -1.0		-1.0 -1.0	V V	$I_C = -10mA, I_B = -1mA$ $I_C = -50mA, I_B = -5mA$
Transition Frequency	$f_T$	100	400	100	300	MHz	$I_C = -10mA, V_{CE} = -10V$ $f = 100MHz$
Output Capacitance	$C_{obo}$		6.0		6.0	pF	$V_{CB} = -10V, f = 1MHz$
Small Signal	$h_{fe}$	30	200	40	260		$I_C = -1mA, V_{CE} = -10V$ $f = 1KHz$ †
Noise Figure	NF		8		8	dB	$I_C = -250\mu A, V_{CE} = -5V,$ $R_S = 1K\Omega$ $f = 10Hz$ to $15.7KHz$

† Periodic Sample Test Only



LittleDiode supplies new, hard to find or obsolete electronic components and semiconductors all over the world.

With over two million different components listed you are sure to find the part you need.

Feel free to visit us today at our online store:

[LittleDiode.com](http://LittleDiode.com)

Looking forward to providing you with the best possible service.